


BOCA RESEARCH, INC.
BOCAMODEM M024ID

Modem Type Data (asynchronous)
Maximum Data Rate 2400bps
Data Bus 8-bit ISA
Data Modulation Protocol Bell 103A/212A
 ITU-T V.22, V.22bis
Error Correction/Compression Unidentified



CONNECTIONS			
Purpos	Location	Purpos	Location
Line out	CN1	Line in	CN2

BASE I/O ADDRESS SELECTION				
Port	JP1/A	JP1/B	JP1/C	JP1/D
COM1: (3F8h)	Closed	Open	Open	Open
COM2: (2F8h)	Open	Closed	Open	Open
COM3: (3E8h)	Open	Open	Closed	Open
COM4: (2E8h)	Open	Open	Open	Closed

INTERRUPT SELECTION				
IRQ	JP1/E	JP1/F	JP1/G	JP1/H
3	Closed	Open	Open	Open
4	Open	Closed	Open	Open
5	Open	Open	Closed	Open
7	Open	Open	Open	Closed

Continued on next page . . .

Proprietary AT Command Set

BIT-MAPPED REGISTERS	
Registers	Default
S14	138
S21	4
S22	117
S23	55
S27	73
S28	0

PROTOCOL/SPEED	
Type:	Register
Format	AT [cmds] S19= <i>n</i> [cmds]
Example:	ATS19=0<CR>
Default:	0
Range:	Unidentified
Unit:	Unidentified
Description:	Selects the current protocol and speed.

SLEEP TIMER	
Type:	Register
Format	AT [cmds] S24= <i>n</i> [cmds]
Example:	ATS24=0<CR>
Default:	0
Range:	Unidentified
Unit:	Unidentified
Description:	Maximum duration of DTE and DCE inactivity allowed prior to initiating low-power sleep mode.

BOCA RESEARCH, INC.
 BOCAMODEM M024ID

...continued from previous page

TEST MODES		
Type:	Register	
Format	AT [cmds] S16= <i>n</i> [cmds]	
Example:	ATS16=0<CR>	
Default:	0	
Range:	0-125	
Unit:	Bit-mapped	
Description:	Controls loopback tests, analog, digital, remote digital, and self tests.	
Bit	Value	Function
0	0	Local analog loopback not in progress.
	1	Local analog loopback in progress.
1	0	Not used.
2	0	Local digital loopback not in progress.
	1	Local digital loopback in progress.
3	0	Modem not in remote digital loopback.
	1	Remote digital loopback in progress.
4	0	Remote digital loopback not requested.
	1	Remote digital loopback requested.
5	0	Remote digital loopback w/ self-test not in progress.
	1	Remote digital loopback w/ self-test in progress.
6	0	Local analog loopback w/ self-test not in progress.
	1	Local analog loopback w/ self-test in progress.