


SUNIX CO., LTD.

SUN-6304HT (EX-4041)

Card Type	Serial card
Chip Set	LGS/GM16C550
Maximum Onboard Memory	None
I/O Options	Serial ports (4)
Data Bus	16-bit ISA
Floppy drives supported	None



CONNECTIONS			
Function	Location	Function	Location
9-pin serial port 1	S1	10-pin serial port 3	S3
25-pin serial port 2	S2	10-pin serial port 4	S4

SERIAL PORT 1 ADDRESS SELECTION								
COM	JP1/1	JP1/2	JP1/3	JP1/4	JP1/5	JP1/6	JP1/7	JP1/8
COM1(3F8h)	Closed	Open	Open	Open	Open	Open	Open	Open
COM2(2F8h)	Open	Closed	Open	Open	Open	Open	Open	Open
COM3(3E8h)	Open	Open	Closed	Open	Open	Open	Open	Open
COM4(2E8h)	Open	Open	Open	Closed	Open	Open	Open	Open
COM5(3F0h)	Open	Open	Open	Open	Closed	Open	Open	Open
COM6(3E0h)	Open	Open	Open	Open	Open	Closed	Open	Open
COM7(2E0h)	Open	Open	Open	Open	Open	Open	Closed	Open
COM8(260h)	Open	Open	Open	Open	Open	Open	Open	Closed

SERIAL PORT 2 ADDRESS SELECTION								
COM	JP2/1	JP2/2	JP2/3	JP2/4	JP2/5	JP2/6	JP2/7	JP2/8
COM1(3F8h)	Closed	Open	Open	Open	Open	Open	Open	Open
COM2(2F8h)	Open	Closed	Open	Open	Open	Open	Open	Open
COM3(3E8h)	Open	Open	Closed	Open	Open	Open	Open	Open
COM4(2E8h)	Open	Open	Open	Closed	Open	Open	Open	Open
COM5(3F0h)	Open	Open	Open	Open	Closed	Open	Open	Open
COM6(3E0h)	Open	Open	Open	Open	Open	Closed	Open	Open
COM7(2E0h)	Open	Open	Open	Open	Open	Open	Closed	Open
COM8(260h)	Open	Open	Open	Open	Open	Open	Open	Closed

Continued on next page. . .

SUNIX CO., LTD.
 SUN-6304HT (EX-4041)

...continued from previous page

SERIAL PORT 3 ADDRESS SELECTION								
COM	JP3/1	JP3/2	JP3/3	JP3/4	JP3/5	JP3/6	JP3/7	JP3/8
COM1(3F8h)	Closed	Open	Open	Open	Open	Open	Open	Open
COM2(2F8h)	Open	Closed	Open	Open	Open	Open	Open	Open
COM3(3E8h)	Open	Open	Closed	Open	Open	Open	Open	Open
COM4(2E8h)	Open	Open	Open	Closed	Open	Open	Open	Open
COM5(3F0h)	Open	Open	Open	Open	Closed	Open	Open	Open
COM6(3E0h)	Open	Open	Open	Open	Open	Closed	Open	Open
COM7(2E0h)	Open	Open	Open	Open	Open	Open	Closed	Open
COM8(260h)	Open	Open	Open	Open	Open	Open	Open	Closed

SERIAL PORT 4 ADDRESS SELECTION								
COM	JP4/1	JP4/2	JP4/3	JP4/4	JP4/5	JP4/6	JP4/7	JP4/8
COM1(3F8h)	Closed	Open	Open	Open	Open	Open	Open	Open
COM2(2F8h)	Open	Closed	Open	Open	Open	Open	Open	Open
COM3(3E8h)	Open	Open	Closed	Open	Open	Open	Open	Open
COM4(2E8h)	Open	Open	Open	Closed	Open	Open	Open	Open
COM5(3F0h)	Open	Open	Open	Open	Closed	Open	Open	Open
COM6(3E0h)	Open	Open	Open	Open	Open	Closed	Open	Open
COM7(2E0h)	Open	Open	Open	Open	Open	Open	Closed	Open
COM8(260h)	Open	Open	Open	Open	Open	Open	Open	Closed

SERIAL PORT 1 INTERRUPT SELECTION									
IRQ	JP5/A	JP5/B	JP5/C	JP5/D	JP5/E	JP5/F	JP5/G	JP5/H	JP5/I
IRQ3	Closed	Open	Open	Open	Open	Open	Open	Open	Open
IRQ4	Open	Closed	Open	Open	Open	Open	Open	Open	Open
IRQ5	Open	Open	Closed	Open	Open	Open	Open	Open	Open
IRQ7	Open	Open	Open	Closed	Open	Open	Open	Open	Open
IRQ9	Open	Open	Open	Open	Closed	Open	Open	Open	Open
IRQ10	Open	Open	Open	Open	Open	Closed	Open	Open	Open
IRQ11	Open	Open	Open	Open	Open	Open	Closed	Open	Open
IRQ12	Open	Open	Open	Open	Open	Open	Open	Closed	Open
IRQ15	Open	Open	Open	Open	Open	Open	Open	Open	Closed

SERIAL PORT 2 INTERRUPT SELECTION									
IRQ	JP6/A	JP6/B	JP6/C	JP6/D	JP6/E	JP6/F	JP6/G	JP6/H	JP6/I
IRQ3	Closed	Open	Open	Open	Open	Open	Open	Open	Open
IRQ4	Open	Closed	Open	Open	Open	Open	Open	Open	Open
IRQ5	Open	Open	Closed	Open	Open	Open	Open	Open	Open
IRQ7	Open	Open	Open	Closed	Open	Open	Open	Open	Open
IRQ9	Open	Open	Open	Open	Closed	Open	Open	Open	Open
IRQ10	Open	Open	Open	Open	Open	Closed	Open	Open	Open
IRQ11	Open	Open	Open	Open	Open	Open	Closed	Open	Open
IRQ12	Open	Open	Open	Open	Open	Open	Open	Closed	Open
IRQ15	Open	Open	Open	Open	Open	Open	Open	Open	Closed

Continued on next page...

