


# UNIDENTIFIED SMART EK

**Processor** 80286  
**Processor Speed** 6/8MHz  
**Chip Set** None  
**Max. Onboard DRAM** 1MB  
**Cache** None  
**BIOS** SMT  
**Dimensions** 350mm x 304mm  
**I/O Options** None  
**NPU Options** 80287



CONNECTIONS			
Purpose	Location	Purpose	Location
Speaker	J19	External battery	J21
Power LED & keylock	J20	Reset switch	E5

Continued on next page...

# UNIDENTIFIED SMART EK

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper/Switch	Position
Speed select high speed	E1	Closed
Speed select low speed	E1	Open
Memory wait state select 0 wait states	E2	Closed
Memory wait state select 1 wait state	E2	Open
Turbo select high	J3	Open
Turbo select low	J3	Closed
Turbo select software	J3	Ctrl, Alt, -
í Monitor type select color	SW1	Off
Monitor type select monochrome	SW1	On

Note: The location of E2 is unidentified.

DRAM CONFIGURATION		
Size	Bank 0	Bank 1
512KB	(18) 41256	NONE
640KB	(18) 41256	(18) 4164
1MB	(18) 41256	(18) 41256

DRAM JUMPER CONFIGURATION		
Size	E3	E4
512KB	Open	Closed
640KB	Closed	Open
1MB	Open	Open

Note: The location of E3 is unidentified.