


UNIDENTIFIED A PLUS SUPER TURBO

Processor 8088
Processor Speed 4.77/10/12MHz
Chip Set Unidentified
Max. Onboard DRAM 1MB
Cache None
BIOS Unidentified
Dimensions 254mm x 218mm
I/O Options None
NPU Options 8087



CONNECTIONS			
Purpose	Location	Purpose	Location
Power LED	CN3	Keylock	CN6
Reset switch	CN4	Turbo LED	CN7
Speaker	CN5	Turbo switch	CN8

Continued on next page. . .

UNIDENTIFIED A PLUS SUPER TURBO

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper/Switch	Position
CPU speed select 4.77MHz	CN8	Open
CPU speed select 10/12MHz	CN8	Closed
í DRAM wait state select 0 wait states	J6	Open
DRAM wait state select 1 wait state	J6	Closed
Parity disabled	SWA/1	On
Parity enabled	SWA/1	Off
í Factory configured - do not alter	SWA/2	On

DRAM CONFIGURATION	
Size	
512KB	
640KB	
1MB	
Note: The actual Bank 0, Bank 1 and parity locations are unidentified. The size of the chips are unidentified.	

DRAM SWITCH CONFIGURATION		
Size	SWA/3	SWA/4
None	On	On
512KB	Off	On
640KB	On	Off
1MB	Off	Off

VIDEO CONFIGURATION		
Setting	SWA/5	SWA/6
None	On	On
CGA (40 x 25)	Off	On
CGA (80 x 25)	On	Off
Monochrome	Off	Off

FLOPPY DRIVE CONFIGURATION		
Drives installed	SWA/7	SWA/7
1	On	On
2	Off	On
3	On	Off
4	Off	Off