

663AS PRO

使 用 手 冊

AMD Socket A Athlon/Duron 處理器主機板

編號. G03-663ASP1C

發佈日期 2000 年 11 月

** 遵循2000年電腦規格 **

商標:

- * Athlon 和 Duron 都是 AMD 公司的註冊商標。其他商標及名稱皆屬其所屬公司所有。
 - * 包含在此文件之規格及資料僅為使用資訊的提供，任何修改將不另行通知，並且不應視為廠商的承諾。
-
-

目 錄

| | |
|-------------|---|
| 使用者需知..... | 1 |
| 手冊版本資訊..... | 2 |
| 散熱解決方案..... | 2 |

第一章 663AS PRO 主機板簡介

| | |
|-------------------|---|
| 1-1 主機板特性..... | 3 |
| 1-2 規格..... | 4 |
| 1-3 性能表..... | 5 |
| 1-4 設計圖及跳線設定..... | 6 |

第二章 硬體安裝

| | |
|---|----|
| 2-1 硬體安裝步驟..... | 8 |
| 2-2 檢查主機板的跳線設置..... | 8 |
| 2-3 安裝CPU..... | 8 |
| 2-3-1 關於AMD Athlon 及Duron™ 462-腳座CPU..... | 8 |
| 2-3-2 安裝CPU..... | 10 |
| 2-4 安裝記憶體..... | 10 |
| 2-5 擴充卡..... | 11 |
| 2-5-1 擴充卡安裝程序..... | 11 |
| 2-5-2 為擴充卡指定IRQ..... | 12 |
| 2-5-3 主機板的中斷列表..... | 12 |
| 2-5-4 AGP 插槽..... | 13 |
| 2-6 連接埠・接頭..... | 13 |
| 2-6-1 連接埠..... | 13 |
| 2-6-2 接頭..... | 16 |
| 2-7 啟動你的電腦..... | 18 |

CHAPTER 3 BIOS介紹

| | |
|------------------------------------|----|
| 3-1 進入SETUP..... | 20 |
| 3-2 線上說明..... | 21 |
| 3-3 主目錄..... | 21 |
| 3-4 STANDARD CMOS FEATURES..... | 22 |
| 3-5 ADVANCED BIOS FEATURES..... | 24 |
| 3-6 ADVANCED CHIPSET FEATURES..... | 26 |
| 3-6-1 ADVANCED DRAM CONTROL..... | 28 |
| 3-6-2 ADVANCED AGP CONTROL..... | 29 |
| 3-7 INTEGRATED PERIPHERALS..... | 29 |
| 3-7-1 ONCHIP IDE FUNCTION..... | 30 |

| | |
|------------------------------------|----|
| 3-7-2 ONCHIP DEVICE FUNCTION..... | 31 |
| 3-7-2.1 ONCHIP AUDIO FUNCTION..... | 32 |

i

| | |
|--|----|
| 3-7-3 ONCHIP SUPERIO FUNCTION..... | 32 |
| 3-8 POWER MANAGEMENT SETUP..... | 34 |
| 3-8-1 POWER MANAGEMENT..... | 35 |
| 3-8-2 WAKE UP EVENTS..... | 36 |
| 3-8-2.1 IRQS ACTIVITY MONITORING..... | 37 |
| 3-9 PNP/PCI CONFIGURATION SETUP..... | 37 |
| 3-10 PC HEALTH STATUS..... | 38 |
| 3-11 FREQUENCY/VOLTAGE CONTROL | 39 |
| 3-12 LOAD STANDARD/OPTIMIZED DEFAULTS..... | 40 |
| 3-13 SET SUPERVISOR/USER PASSWORD..... | 40 |

第四章 驅動程式及免費軟體的安裝

| | |
|---|----|
| 支援WINDOWS 95/98/98SE/NT4.0/2000 的MAGIC INSTALL..... | 41 |
| 4-1 IDE 安裝 VIA 四合一驅動程式..... | 42 |
| 4-2 PC-HEALTH 安裝 VIA 的硬體監控程式..... | 44 |
| 4-2-1 如何使用 VIA 硬體監控程式..... | 44 |
| 4-3 SOUND 安裝 VIA AC'97音效裝置的驅動程式..... | 45 |
| 4-4 PC-CILLIN 安裝 PC-CILLN98 防病毒程式..... | 46 |
| 4-5 如何關閉內建式音效卡..... | 47 |
| 4-6 怎樣更新 BIOS | 47 |

使用者需知

本手冊的版權屬於其製造廠商。其中的任何部分（包括所描述之產品和軟體）都不允許在未經其製造廠商書面授權的情況下以任何形式或者採取任何方法複製、傳播或翻譯成任何語言。

本手冊包含了使用 663AS PRO 主機板所必須的所有資訊，並且我們確保本手冊能完全滿足使用者的需求，如有任何改變或修正將不另行通知。廠商提供本手冊是不帶任何方式的擔保，而且將不對一切直接的、間接的、特殊的、偶然的或是因此而產生的損害（包括利潤損失，商業損失，使用數據時的損失，商業中斷等等）負責。

本手冊所使用的產品名稱及公司名稱可能不是其註冊商標或其註冊版權。僅用於說明或解釋之作用，並無意侵犯其所有者的權益。

手冊版本資訊

| | | |
|-----|------|-------------|
| 版本 | 版本記錄 | 日期 |
| 1.0 | 第一版 | 2000 年 11 月 |

項目表

- 663AS PRO
- IDE/Floppy 排線
- 主機板應用程式光碟片
- USB Port 3/4 排線(可選購)
- COM2 排線
- 663AS PRO 使用手冊

AMD-Duron™ 中央處理器的散熱解決方案 - 風扇

由於科技的日新月異，中央處理器 (CPU) 亦持續往更快速、更高的效能發展。因此在建置電腦系統時，散熱的處理變得越來越重要了，一個適當的散熱環境，是讓系統更加穩定及長期操作時的關鍵。提供適當散熱環境的最終目的，則在於維持中央處理器之溫度，能低於電腦機殼之最大特定溫度。

一個好的風扇，除了要有較高的轉速外，適當的散熱片面積亦是相當重要的因素。它可透過其表面之散熱片區域的範圍，集中來自中央處理器的高熱，並透過附加的風扇讓熱氣流傳導出去。除此之外，散熱膏亦能有效的將高熱由中央處理器傳輸到散熱片。為了達到散熱傳導的最佳效果，AMD 建議您使用散熱膏，並以固定夾將風扇附加在處理器上。

當您為系統選擇適當的風扇時，請參考以下網址中 AMD 所推薦與 AMD 處理器一起使用之風扇。

有關 AMD Athlon / Duron 處理器之散熱片及風扇銷售廠商，請至以下網址：
<http://www1.amd.com/products/duron/thermals>

第一章

663AS PRO 主機板簡介

1-1 主機板特性

663AS PRO 是為使用 AMD 新一代 Athlon/Duron 處理器而設計，採用 Socket-A 封裝設計且記憶體可擴充至 1.5GB。

此主機板此用最新的 VIA KT-133 晶片組，其 100MHz 前端匯流排頻率 (200MHz 使用 Double Data Rate，雙倍資料傳輸率) 及 133MHz 記憶體介面提供了一條通往 100MHz 處理器和 PC-133 SDRAM 的升級途徑。同時，它還提供了 ULTRA ATA 100 介面以支援 ATA-100 的硬碟，全面提高系統性能。

663AS PRO 還具有內建式整合型 AC'97 2.1 CODEC，能與 Sound Blaster Pro® 完全相容，給你帶來最佳音效品質及相容性。另外，對那些需要更強大圖像性能的使用者，663AS PRO 則提供有 AGP 4X 模式的插槽供使用者使用。

663AS PRO 具有 2 個 USB 介面，可連結 4 個 USB 裝置，足以迎合未來對 USB 的需求。而且本主機板含有內建的硬體監控功能，可監控並保護你的電腦。

另外，本主機板除了提供有標準的 Synchronous DRAM (SDRAM) 記憶體介面，它還可支援 Virtual Channel Memory SDRAM (VCM SDRAM) 的記憶體介面，讓使用者有更具彈性的選擇。

該主機板除了提供有高階的性能，還同時滿足未來規範的需要，確實是您購買主機板的最佳選擇。

1-2 規格

| 規 格 | 說 明 |
|------|---------------------------------|
| 設計尺寸 | * ATX 主機板架構，4層板，尺寸：30.5 x 21 釐米 |
| 晶片組 | * VIA KT-133 Chipset |

| | |
|------------------|--|
| CPU插座 | <ul style="list-style-type: none"> * AMD Athlon 700~1GHz 處理器 * AMD Duron 600~750MHz 處理器 * 支援 100MHz F.S.B. * 支援 200MHz (Double Data Rate) * 預留對未來 AMD Athlon/Duron 處理器的支援 |
| 記憶體插座 | <ul style="list-style-type: none"> * 168-針 DIMM 插座 x 3 * PC-100/PC-133 SDRAM/Virtual Channel Memory SDRAM (VCM SDRAM) * 可擴充至 1.5GB * 支援 3.3V SDRAM DIMM |
| 擴充插槽及接頭 | <ul style="list-style-type: none"> * AGP 插槽 x 1 · 支援 AGP 2.0 & 4X 模式 * 5 個 32 位元 PCI 插槽 * 1 個 AMR 插槽 * 1 個 ISA 插槽 |
| 整合型 IDE | <ul style="list-style-type: none"> * 2個支援ULTRA DMA 33/66/100 的 Bus Master IDE 埠 |
| 音效 | <ul style="list-style-type: none"> * 整合型AC'97數位式音效控制器 * 內建 AC'97 Audio CODEC * 包含音效卡驅動程式及應用程式 |
| BIOS | <ul style="list-style-type: none"> * Award 2MB Flash ROM |
| Multi I/O | <ul style="list-style-type: none"> * PS/2滑鼠和 PS/2 鍵盤介面 * 1個軟碟驅動器 * 1個並列埠 * 2個串列埠 * 2個USB介面 * 2個USB 接頭 (排線為選購性配備) * 音效介面 (輸入、輸出及搖桿介面) |

1-3 性能表

下列性能數據表是某些較為流行之基本測試程式的測試結果。這些數據僅供使用者參考，而且我們不保証與使用者自行測得的數值完全吻合（不同的硬軟體配置將導致不同的測試結果）。


CPU: AMD K7 900MHz

記憶體: 128M SDRAM x2 (Hyundai GM 72V66841ET75)
 128M PC-133 VCM SDRAM x2 (NEC D4565821G5)
VGA 擴充卡: Geforce 256 (1024x768 Hi-color) Driver V3.68
硬碟: Quantum Fireball KX20A11
BIOS: Award Optimal default
操作系統: Win 98SE
A: PC-133 SDRAM
B: VCM SDRAM

Performance Test Report

| | PC-133 SDRAM | | VCM SDRAM | |
|--|--------------|---------|-----------|---------|
| | 100/100 | 100/133 | 100/100 | 100/133 |
| 3D Mark 99 | 5848 | 5849 | 5820 | 5853 |
| 3D Mark 2000 | 4187 | 4213 | 4163 | 4207 |
| 3D Winbench 99 V1.2 | 899 | 900 | 899 | 900 |
| 3D Winbench 2000 | 79.2 | 80.1 | 78.7 | 80.2 |
| Final Reality | 6.32 | 6.30 | 6.27 | 6.52 |
| Winstone 99 V1.3 | 32.7 | 32 | 32 | 32.1 |
| Winstone 2000 | 37.6 | 37.3 | 36.7 | 37.2 |
| Winbench 99 : | | | | |
| CPU Mark 99 | 82 | 82.5 | 80.2 | 82 |
| FPU Winmark 99 | 4920 | 4920 | 4920 | 4920 |
| Business Disk Winmark99 | 4860 | 4820 | 4810 | 4940 |
| Hi-end Disk Winmark99 | 17000 | 16900 | 16900 | 17000 |
| Business Graphic Winmark | 419 | 420 | 416 | 420 |
| Hi-end Graphic Winmark | 1230 | 1240 | 1220 | 1250 |
| SYS Mark 2000 : SISMark 2000 Rating (Internet Content Creation / Office Productivity) | | | | |
| Suites | 184 | 183 | 179 | 184 |
| Official | 182 | 182 | | |
| SISOFT Sandra 2000 : | | | | |
| CPU MIPS | 2830 | 2814 | 2826 | 2821 |
| FPU MFLOPS | 1213 | 1257 | 1213 | 1213 |
| CPU / Memory MB/S | 391 | 417 | 413 | 470 |
| FPU / Memory MB/S | 422 | 500 | 460 | 565 |
| QUAKE3 : | | | | |
| DEMO1 FPS | 103.5 | 105.0 | 99.7 | 104.6 |
| DEMO2 FPS | 100.7 | 102.5 | 97.0 | 102.1 |
| | BY SPD | BY SPD | BY SPD | BY SPD |

1-4 設計圖及跳線設定



跳線

| Jumper | Name | Description | Page |
|--------|---------|-------------|------|
| JBAT | 清除 CMOS | 3-pin Block | p.8 |

連接器

| Connector | Name | Description | Page |
|-----------|--------------------|---------------------------------|------|
| CN1 | ATX 電源介面 | 20-pin Block | p.13 |
| PS1 | PS/2 滑鼠及 PS/2 鍵盤介面 | 6-pin Female | p.13 |
| USB1 | USB 埠介面 | 4-pin Connector | p.14 |
| CN2 | 並列埠介面 | 25-pin Female | p.14 |
| AUD_GAME1 | 音效及遊戲埠介面 | 3 phone jack + 15-pin Connector | p.14 |
| COM1 | 串列埠介面 | 9-pin Connector | p.14 |
| FDD1 | 軟碟介面 | 34-pin Block | p.15 |
| IDE1 | 第一個 IDE 介面 | 40-pin Block | p.15 |
| IDE2 | 第二個 IDE 介面 | 40-pin Block | p.16 |

接頭

| Header | Name | Description | Page |
|---------------|------------------|--------------|------|
| COM2 | COM2 通信接頭 | 10-pin Block | p.16 |
| J5 | USB Port 介面 | 10-pin Block | p.16 |
| IDELED | IDE Activity LED | 2-pin Block | p.16 |
| TBLED | Turbo LED 開關 | 2-pin Block | p.16 |
| RESET | Reset 開關 | 2-pin Block | p.16 |
| SPKR | 喇叭線連接頭 | 4-pin Block | p.16 |
| PWR LED | 電源 LED | 2-pin Block | p.16 |
| PW BN | 電源開關 | 2-pin Block | p.17 |
| WOL1 | 遠程網路啟動介面 | 3-pin Block | p.17 |
| FAN1,FAN2 | 風扇電源接頭 | 3-pin Block | p.17 |
| IR1 | IR 紅外線介面 | 5-pin Block | p.18 |
| CD_IN1,CD_IN2 | CD 音效輸入介面 | 4-pin Block | p.18 |

擴充插槽

| Socket/Slot | Name | Description | Page |
|---------------------------------|------------------|--|------|
| ZIF Socket 462 | CPU 插槽 | 462-pin PPGA CPU Socket | p.10 |
| DIMM1, DIMM2 DIMM3 | DIMM Module 擴充插槽 | 168-pin DIMM SDRAM Module Expansion Socket | p.10 |
| PCI1, PCI2, PCI3, PCI4, PCI5 | PCI 擴充插槽 | 32-bit PCI Local Bus Expansion slots | p.12 |
| AGP | AGP 4X 模式插槽 | AGP Expansion Slot | p.12 |
| ISA | ISA 插槽 | 16-bit ISA BUS Expansion Slot | p.12 |

第二章

硬體安裝

2-1 硬體安裝步驟

在使用你的電腦之前，你必須完成下列步驟：


1. 檢查主機板設定
2. 安裝CPU
3. 安裝記憶體
4. 安裝擴充卡
5. 連接排線，面板電線及電源
6. 設定BIOS參數
7. 安裝軟體驅動程式及應用程式

2-2 檢查主機板的跳線設置

1. 清除 CMOS (3-pin) : JBAT

主機板必須使用一個電池將主機板的配置資料保存在CMOS RAM裡，再透過跳帽將JBAT的1-2腳短路來存儲CMOS數據。

注意！ 當系統斷電時，你可以將2-3腳短路來清除CMOS數據。然後再放回短接1-2腳。在系統通電時，切勿清除CMOS，亦不可突然拔掉電源線以避免導致主機板損壞。



2-3 安裝 CPU

2-3-1 關於 AMD Athlon & Duron 462-腳位 CPU

此主機板可支援 Socket-A (Socket-462) AMD Athlon/Duron 處理器。

常用術語：

晶片組(Chipset (or core logic)) - two or more integrated circuits which control the interfaces between the system processor, RAM, I/O devices, and adapter cards.

處理器插槽 / 插座 (Processor slot/socket) - the slot or socket used to mount the system processor on the motherboard.

擴充插槽 (Slot (AGP, PCI, ISA, RAM)) - the slots used to mount adapter cards and system

RAM.

AGP 擴充槽 (Accelerated Graphics Port) - a high speed interface for video cards; runs at 1X (66MHz), 2X (133MHz), or 4X (266MHz).

PCI 擴充槽 (Peripheral Component Interconnect) - a high speed interface for video cards, sound cards, network interface cards, and modems; runs at 33MHz.

ISA 擴充槽 (Industry Standard Architecture) - a relatively low speed interface primarily used for sound cards and modems; runs at approx. 8MHz.

串列埠 (Serial Port) - a low speed interface typically used for mouse and external modems.

並列埠 (Parallel Port) - a low speed interface typically used for printers.

PS/2 - a low speed interface used for mouse and keyboards.

USB - Universal Serial Bus - a medium speed interface typically used for mouse, keyboards, scanners, scanners, and some digital cameras.

音效裝置 (Sound) - the interface between the sound card or integrated sound connectors and speakers, mic, game controllers, and MIDI sound devices.

區域性網路 (LAN) - Local Area Network - the interface to your local area network.

基本輸出/輸入系統 (BIOS ; Basic Input/Output System) - the program logic used to boot up a computer and establish the relationship between the various components.

驅動程式(Driver) - software, which defines the characteristics of a device for use by another device or other software.

中央處理器(Processor) - the "central processing unit" (CPU); the principal integrated circuit used for doing the "computing" in "personal computer"

前端匯流排頻率 (Front Side Bus Frequency)

The working frequency of the motherboard, which is generated by the clock generator for CPU, DRAM and PCI BUS.

CPU L2 快取記憶體 (CPU L2 Cache)


The flash memory inside the CPU, normal Athlon CPU has 256K or above, while Duron CPU has 64K 。

2-3-2 安裝 CPU

此主機板提供了一個 ZIP Socket-A 的插座。安裝在主機板上的 CPU 必須裝有風扇以防止 CPU 過熱。如果你尚未購買風扇，請在安裝系統前請購買一個合適的風扇。

| | |
|-------------|---|
| 警告 ! | 請確保處理器之散熱片的表面有充足的空氣流通，且CPU冷卻風扇工作正常。否則將使處理器和主機板因過熱而造成損壞。如果需要的話你可以另外安裝輔助風扇。 |
|-------------|---|

安裝 CPU 前，先請關閉你的系統再移除外殼。找到 ZIF 插槽並先從插槽一側拉起拉桿使之向上成90度。將CPU從如下圖所示的正確方位插入。有凹口的一角應該朝向拉桿的末端。因為CPU四個角中有兩角缺了一個引腳，因此會適合於如圖所示的方位。



當你將CPU插入ZIF插槽時，不要使用太大的力量，插入後只要輕輕把拉桿沿正確方向按下即可。

2-4 安裝記憶體

此主機板提供有三個168-針 Dual Inline Memory Module (DIMM) 插槽，可使記憶體從最小的 32MB 擴充至最大的 1.5GB 記憶體。

有效記憶體配置

| Bank | 168-Pin DIMM | | Total Memory |
|-------------------|-------------------------------|----|--------------|
| Bank 0, 1 (DIMM1) | SDRAM 32, 64, 128, 256, 512MB | X1 | 32MB~512MB |
| Bank 2, 3 (DIMM2) | SDRAM 32, 64, 128, 256, 512MB | X1 | 32MB~512MB |
| Bank 4, 5 (DIMM3) | SDRAM 32, 64, 128, 256, 512MB | X1 | 32MB~512MB |
| Total | System Memory (Max. 1.5GB) | | 32MB~1.5GB |

注意！ 請確認所安裝的所有記憶體不超過 1.5GB，否則，系統將可能在啟動時發生錯誤。

一般來說，將記憶體安裝到主機板上是非常容易的，你可以參考圖2-4安裝記憶體的簡圖。




圖 2-4

注意！ 當你將DIMM記憶體完全插入DIMM插槽時，請將兩端的白色護耳緊緊地卡好使其恰好卡住兩端的凹口。

警告！ 如果SDRAM頻率設為133MHz 時，祇能使用PC133-相容的DIMM。當此主機板設成133MHz時，如果您的DIMM不是PC133-相容的話，會由於嚴格的同步問題，導致系統無法啟動。如有這種現象，請將頻率設為100MHz以確保系統的穩定性。

2-5 擴充卡

警告！ 當添加、移除擴充卡，或其他系統組件時務必請關掉電源，以避免對主機板和擴充卡造成損害。

2-5-1 擴充卡安裝程序

1. 仔細閱讀擴充卡所附之文件，將所有相關之必要的軟、硬體設定好，比如跳線。
2. 移除電腦外殼，並將你想要安裝之插槽處的金屬支架拆除。
3. 將該擴充卡插入並穩固地壓下去。
4. 鎖上螺絲。
5. 將系統機殼放回原位。
6. 如果有必要，請在 BIOS內設定其參數。
7. 安裝擴充卡所須的相關驅動程式。

2-5-2 設定擴充卡的 IRQ

某些擴充卡需要指定 IRQ 方可使用。一般來說，每一個 IRQ 的埠口位址祇能單獨地指定給某一個裝置使用。在標準設計中，有16個IRQ是可用的，但其中的大部分都已被系統使用中。

IRQ 的基本中斷分配表

| IRQ | Priority | Standard function |
|------|----------|-----------------------------|
| 0 | N/A | System Timer |
| 1 | N/A | Keyboard Controller |
| 2 | N/A | Programmable Interrupt |
| 3 * | 8 | Communications Port (COM2) |
| 4 * | 9 | Communications Port (COM1) |
| 5 * | 6 | Sound Card (sometimes LPT2) |
| 6 * | 11 | Floppy Disk Controller |
| 7 * | 7 | Printer Port (LPT1) |
| 8 | N/A | System CMOS/Real Time Clock |
| 9 * | 10 | ACPI Mode when enabled |
| 10 * | 3 | IRQ Holder for PCI Steering |
| 11 * | 2 | IRQ Holder for PCI Steering |
| 12 * | 4 | PS/2 Compatible Mouse Port |
| 13 | N/A | Numeric Data Processor |
| 14 * | 5 | Primary IDE Channel |
| 15 * | 1 | Secondary IDE Channel |

*上述的 IRQ 通常可供 ISA 或 PCI 介面裝置使用。

2-5-3 主機板的中斷列表


主機板共用的中斷指令如下表所示：

| | INT A | INT B | INT C | INT D |
|---------------|--------|--------|------------|--------|
| PCI slot 1 | Shared | — | — | — |
| PCI slot 2 | — | Shared | — | — |
| PCI slot 3 | — | — | Not Shared | — |
| PCI slot 4 | — | — | — | Shared |
| PCI slot 5 | Shared | — | — | — |
| AGP slot | Shared | — | — | — |
| AC97/MC97 | — | — | Shared | — |
| Onboard USB 0 | — | — | — | Shared |
| Onboard USB 1 | — | — | — | Shared |

重要！ 如果你在共用的插槽上使用PCI卡，請確認驅動程式可支援”Shared IRQ”或者該卡不需要分配任何IRQ。否則兩個PCI組之間將產生衝突，進而使得整個系統不穩定而且PCI卡將不可使用。

2-5-4 AGP 插槽

此主機板提供有一個可支援 1X/2X/4X 模式的 AGP 顯示卡插槽。




2-6 連接埠, 接頭

2-6-1 連接埠


(1) 電源介面 (20-pin block) : CN1

此為 ATX 電源供應器的介面，其 20-pin 的定義如下表。ATX 電源供應器電源經由個人電腦面板上一個 2-pin 的控制開關來控制電腦電源的開或關。




(2) PS/2 滑鼠及 PS/2 鍵盤介面: PS1

PS/2 滑鼠介面可連接 PS/2 滑鼠，同樣地，PS/2 鍵盤介面也用於連接 PS/2 鍵盤，當您的配備不是PS/2規格，則需經由轉接器式轉接排線，接到主機板。




(3) USB 埠介面: USB1

該 USB 塊可讓兩個 USB 裝置連接到主機板。



(4) 並列埠介面 (25-pin female): CN2

該並列埠介面為一個25針母頭構成，可於BIOS設定中 disable 該並列埠。詳細資料請參閱第三章的“INTEGRATED PERIPHERALS SETUP”。



(5) 音效及遊戲介面: AUD_GAME


音效介面有輸出、輸入、麥克風三個介面。

輸出： 音效輸出至喇叭

輸入： 音效輸入至音效晶片


麥克風： 由麥克風輸入

遊戲介面：是一個15-pin 的D型母頭，可連接搖桿或 MIDI 裝置




(6) 串列埠介面: COM1

COM1 是一個 9-pin D型公頭，該串列埠可經由 BIOS 設定為 disable 或 enable。詳細資料請參閱第三章的“INTEGRATED PERIPHERALS SETUP”。




(7) 軟碟介面 (34-pin block): FDD1

該介面經由一條 34-pin 排線與軟碟連接，一般來說，排線有紅邊的方向與 Pin 1 相應，所以在裝置排線時應將紅邊對應軟碟介面的 Pin 1 方向。




(8) 第一個 IDE 介面 (40-pin block): IDE1

該介面經由一條 40-pin 排線與硬碟連接，同樣地，也是紅邊對介面 Pin 1，本產品所附的 ATA-100 排線可用於連接 ATA-100 硬碟。



(9) 第二個 IDE 介面 (40-pin block): IDE2

該介面為另一個 IDE 裝置介面，同樣可經由排線連接兩個 IDE 裝置。




- 每個連接埠能連接兩個硬碟。第一個 HDD 相當於“Master”，第二個 HDD 相當於“Slave”。
- 為了性能的考慮，我們強烈建議請不要將CD-ROM或DVD-ROM驅動器與硬碟安裝在同一個 IDE 通道上。否則，此通道上的系統性能將會降低。

2-6-2 接頭 (Headers)


(1) COM2 通信口 (10-pin) : COM2

This board has another serial port COM2, it come with cable providing serial port COM2.



(2) USB 擴充埠介面(10-pin) : J5

此接頭是用來連接附加的 USB 介面插頭。透過外加一條可選購的USB排線，即可使用附於面板上的兩個額外USB插頭。



(3) IDE Activity LED: IDELED

將硬碟運轉指示燈連接到電腦機殼的接頭。

(4) Turbo LED 開關: TBLED

主機板加速開關的預設值為"開啟" 狀態。當系統電源開啟時，加速燈會一直亮著。你也可以將電腦機殼的電源 LED 連接到這裡，表示電源開或關的顯示。

(5) Reset 開關: RESET

這個 2-pin 接頭可連接電腦機殼上「reset」的電源線，以達到不關閉系統電源的情況下重啟電腦的目的。

(6) 喇叭連線開關: SPKR


這個 4-pin 接頭可連接電腦機殼上「speaker」的開關，以供機殼上的喇叭使用。

(7) 電源 LED 開關: PWR LED

你可將電腦機殼上的 Power LED 線連到此一開關，當系統電源開啟時，Power LED 的燈就會亮起來。

(8) 電源開關: PW BN


這個 2-pin 接頭可連接電腦機殼上的電源開關，供電腦啟動或關閉使用。



(9) 遠程網路啟動介面 (3-pin) : WOL1


將具有WAKE ON LAN輸出規格的網路卡與該介面連接後，當網路卡收到啟動訊號時即可啟動系統，達到遠端程式控制目的。

注意： 使用此一功能前，請確定 BIOS 中的 Wake On LAN 或 Ring In Wake up 有設定成 enabled 狀態。




(10) 風扇電源接頭 (3-pin) : FAN1, FAN2

這些介面支援 350mA (4.2 瓦)或以下的冷卻風扇，根據風扇生產廠商的不同，電線和插座也會不同。紅線應當是陽極，而黑線則是接地。將風扇接頭插到主機板時，應考慮連接頭的極性。




(11) IR 紅外線介面 (5-pin) : IR1

該介面支援可選購的紅外線無線傳輸以及接收組件。必須在 BIOS setup 中設定其參數以使用 IR 的功能。



(12) CD 音效輸入介面 (4-pin) : CD_IN1, CD_IN2

CD_IN1 和 CD_IN2 為音效輸入訊號介面，可與 CD-ROM 音效輸出連接。



2-7 啟動你的電腦

1. 所有排線都接好之後，蓋上機殼。
2. 請確認所有的開關都是關閉的，然後檢查電源的輸出電壓是否設為正確位置，通常情況下輸入電壓為220V~240V或 110V~120V，這取決於你所處位置的使用電壓。
3. 依照你系統的使用手冊，將電源線連接到位於機殼後部的電源接頭上。
4. 依照下列順序將週邊設備依次打開：
 - a. 顯示器。
 - b. 其他週邊設備 (印表機，掃描器，外接式數據機等等...)。

-
-
- c. 系統電源。在 ATX 電源，你必須先打開電源供應器後方電源開關，然後按位於機殼前面的 ATX 電源開關。
 - 5. 位於機殼前面的電源LED將會點亮。顯示器的LED會亮起，如果系統符合綠色環保省電要求，或具有電源待機特性。當系統啟動後在桔紅色與綠色之間切換，接著系統將執行自我檢測。自我檢測執行時，BIOS將發出嘟嘟聲，同時將相關提示資訊顯示在螢幕上。

如果從開啟電源起的30秒內沒看到任何動靜，系統則可能已經自我檢測失敗。請再次檢查你的跳線設定以及連接設定或是打電話向你的零售商尋求協助。

| 自我檢測響鈴 | 意義 |
|--------------|----------------------|
| 顯示 logo 後一短響 | 系統啟動正常 |
| 不停地響 | 未安裝或未檢測到 DRAM |
| 一聲長響後三聲短響 | 未找到顯示卡或顯示用快取記憶體損壞 |
| 系統工作時發出高頻率響聲 | CPU 過熱 系統處於低頻工作環境 |

- 6. 在電腦啟動其間，如果需要更改 BIOS 設定之任何參數，只要按下<Delete>鍵即可進入BIOS setup，再依照 BIOS SETUP 的線上指示完成相關設定。
- 7. 關閉你的電腦：在關閉電源開關之前，你必須先關閉你的操作系統。如果你是用 ATX 的電源供應器，在退出或關閉操作系統後可以按下電源開關。如果你使用的操作系統是 Windows 9X 版本，按下“開始”按鈕，再按“關機”，然後按“關閉這台電腦 (S)”，Windows 在關閉相關應用程式後，會自動關掉電源。

第三章

BIOS 介紹

BIOS是一段儲存在快讀寫式記憶體 (FLASH ROM) 之基本輸出、入控制程式。該程式是主機板與操作系統間的一架橋樑。電腦啟動時，會先由 BIOS 程式進行控制。首先執行一個稱為 POST (開機自我檢測) 的自我測試，它會偵測所有硬體設備，並確認同步硬體參數。當完成所有檢測時，它才將系統的控制權移交給操作系統 (OS)。由於 BIOS 是硬體與軟體聯繫的唯一通道，所以是系統穩定性的關鍵因素，進而確保系統性能可達到最佳狀態。

如圖 3-1 所示，在BIOS設定程式主目錄中，可看到一些選項。我們將在本章的後面逐步解釋這些選項，首先讓我們先看看你將在此用到之功能鍵的簡單描述：

- 按<Esc> 鍵，可退出 BIOS 設定程式。
- 按↑↓←→ (向上，向下，向左，向右) 鍵，可在主目錄中選擇你想確認或修改的選項。
- 當你想要對選項進行參數設定時請按 Page Up/Page Down 或+/-鍵。
- 當完成對參數的設定後，請按<F10>鍵，儲存修改的參數並退出BIOS設定程式，同時電腦也會自動重新開機。

3-1 進入 Setup

在啟動電源開關並且按住就可以馬上進入Setup 程式。如果你來不及在POST過程中按下鍵順利進入CMOS SETUP，那麼可以透過把電源關掉，然後再打開電源開關，或者是直接按下電腦機殼上的“RESET”按鈕重啟動系統，還是同時按下<Ctrl>,<Alt> 和<Delete> 鍵來以重新啟動電腦，並再按 Del 鍵試一次。如果沒能在正確時間內按下以上所有的鍵，或者系統重新啟動失敗，此時在螢幕上會顯示錯誤訊息如下：

Press <F1> to continue, <Ctrl-Alt-Esc> or to enter Setup

你可按 <F1> 鍵繼續，或按 <Ctrl-Alt-Esc> 組合鍵重新啟動電腦，還是按 鍵，進入 BIOS 設定程式。

3-2 線上說明

主目錄

所選取之設定功能的說明，會以反白方式顯示在螢幕底部。

狀態頁安裝目錄/選項頁安裝目錄

按 F1 鍵，則會彈出一個線上說明的小視窗，該視窗描述了該選項中可用之指令以及可能的選擇。再按<Esc>鍵，則可退出該線上說明視窗。

3-3 主目錄

一旦你進入Award BIOS CMOS Setup，主目錄（圖3-1）會顯示在螢幕中。你可以從14項設定功能選項和兩項退出選項中加以選擇。請使用方向鍵在各選項之間進行選擇，再按<Enter>鍵接受或是進入子目錄。




Figure 3-1

Standard CMOS Features

CMOS 的標準設定。

Advanced BIOS Features

BIOS 特性的進階設定。

Advanced Chipset Features

晶片組參數的進階設定，透過更改其設定之參數，可提高系統性能。

Integrated Peripherals

周邊設備設定。

Power Management Setup

電源管理的設定。

PnP/PCI configurations

PnP（即插即用）與 PCI 匯流排設定。

PC Health Status

該項目顯示系統狀態，如 CPU 溫度、風扇轉速等等。

Frequency/Voltage Control

設定頻率/電壓控制。

Load Optimized Defaults

載入最佳化設定。

Load Standard Defaults

載入原廠的預設值。

Set Supervisor/User Password

設定監督者/使用者密碼。

Save & Exit Setup

儲存 CMOS 的設定，然後退出 **Setup** 程式。

Exit Without Saving

放棄 CMOS 所有的修改，然後退出 **Setup** 程式。

3-4 Standard CMOS Features

The items in Standard CMOS Setup Menu are divided into several categories. Each category includes no, one or more than one setup items. Use the arrow keys to highlight the item and then use the <PgUp> or <PgDn> keys to select the value you want in each item.

CMOS Setup Utility - Copyright(C) 1984-2000 Award Software

Standard CMOS Features

| | | |
|------------------------|-------------------|-----------|
| Date (mm:dd:yy) | Wed, Jul, 26 2000 | Item Help |
| Time (hh:mm:ss) | 17 : 35 : 22 | |
| > IDE Primary Master | Press Enter None | |
| > IDE Primary Slave | Press Enter None | |
| > IDE Secondary Master | Press Enter None | |
| > IDE Secondary Slave | Press Enter None | |
| Drive A | 1.44M, 3.25 in. | |
| Drive B | None | |
| Video | EGA/VGA | |
| Halt On | All,But Keyboard | |
| Base Memory | 640K | |
| Extended Memory | 56320K | |
| Total Memory | 57344K | |

↑ ↓ ←→ Move Enter:Select Item +/-/PU/PD:Value F10:Save ESC:Exit F1:General Help
F5:Previous Values F6:Optimized Defaults F7:Standard Defaults

Date

The date format is <day><month><date><year>.

Day Day of the week, from Sun to Sat, determined by BIOS. Read-only.

Month The month from Jan. through Dec.

Date The date from 1 to 31 can be keyed by numeric function keys.

Year The year depends on the year of the BIOS.

Time

The time format is <hour><minute><second>.

Primary Master/Primary Slave

Secondary Master/Secondary Slave

Press PgUp/<+> or PgDn/<-> to select Manual, None, Auto type. Note that the specifications of your drive must match with the drive table. The hard disk will not work properly if you enter improper information for this category. If your hard disk drive type is not matched or listed, you can use Manual to define your own drive type manually.

If you select Manual, related information is asked to be entered to the following items. Enter the information directly from the keyboard. This information should be provided in the documentation from your hard disk vendor or the system manufacturer.

If the controller of HDD interface is SCSI, the selection shall be "None".

If the controller of HDD interface is CD-ROM, the selection shall be "None"

Access Mode The settings are Auto Normal, Large, and LBA.

Cylinder number of cylinders

Head number of heads

Precomp write precomp

Landing Zone landing zone
Sector number of sectors

3-5 Advanced BIOS Features

| CMOS Setup Utility - Copyright(C) 1984-2000 Award Software | |
|--|----------|
| Advanced BIOS Features | |
| Anti-Virus Protection | Enabled |
| PhoneixNet Support | Disabled |
| CPU Internal Cache | Enabled |
| External Cache | Enabled |
| CPU L2 Cache ECC Checking | Enabled |
| Quick Power On Self Test | Enabled |
| First Boot Device | Floppy |
| Second Boot Device | HDD-0 |
| Third Boot Device | LS120 |
| Boot other Device | Enabled |
| Swap Floppy Drive | Disabled |
| Boot Up Floppy Seek | Enabled |
| Boot Up NumLock Status | On |
| Gate A20 Option | Normal |
| Typematic Rate Setting | Disabled |
| x Typematic Rate (Chars/Sec) | 6 |
| x Typematic Delay (Msec) | 250 |
| Security Option | Setup |
| OS Select For DRAM > 64MB | Non-OS2 |
| HDD S.M.A.R.T. Capability | Disabled |
| Video BIOS Shadow | Enabled |
| C8000-CBFFF Shadow | Disabled |
| CC000-CFFFF Shadow | Disabled |
| D0000-D3FFF Shadow | Disabled |
| D4000-D7FFF Shadow | Disabled |
| D8000-DBFFF Shadow | Disabled |
| DC000-DFFFF Shadow | Disabled |

↑ ↓ ← → Move Enter:Select Item +/- /PU/PD:Value F10:Save ESC:Exit F1:General Help
F5:Previous Values F6:Optimized Defaults F7:Standard Defaults

Anti-Virus Protection

Allows you to choose the VIRUS Warning feature for IDE Hard Disk boot sector protection. If this function is enabled and someone attempt to write data into this area, BIOS will show a warning message on screen and alarm beep.

Disabled (default) No warning message to appear when anything attempts to access the boot sector or hard disk partition table.

Enabled Activates automatically when the system boots up causing a warning message to appear when anything attempts to access the boot sector of hard disk partition table.

CPU Internal Cache

The default value is Enabled.

Enabled (default) Enable cache

Disabled Disable cache

Note: *The internal cache is built in the processor.*

External Cache

Choose Enabled or Disabled. This option enables the Level 2 cache memory.

CPU L2 Cache ECC Checking

Choose Enabled or Disabled. This option enables the Level 2 cache memory ECC (error check correction).

Processor Number Feature

This option is for Pentium® III processor. During Enabled, this will check the CPU Serial number. Disabled this option if you don't want the system to know the Serial number.

Quick Power On Self-Test

This category speeds up Power On Self Test (POST) after you power on the computer. If this is set to Enabled. BIOS will shorten or skip some check items during POST.

Enabled (default) Enable quick POST

Disabled Normal POST

First/Second/Third/Fourth Boot Device

The BIOS attempts to load the operating system from the devices in the sequence selected in these items. The settings are Floppy, LS/ZIP, HDD-0/HDD-1/HDD-3, SCSI, CDROM, LAD and Disabled.

Swap Floppy Drive

Switches the floppy disk drives between being designated as A and B. Default is Disabled.

Boot Up Floppy Seek

During POST, BIOS will determine if the floppy disk drive installed is 40 or 80 tracks. 360K type is 40 tracks while 760K, 1.2M and 1.44M are all 80 tracks.

Boot Up NumLock Status

The default value is On.

On (default) Keypad is numeric keys.

Off Keypad is arrow keys.

Gate A20 Option

Normal The A20 signal is controlled by keyboard controller or chipset hardware.

Fast (default) The A20 signal is controlled by port 92 or chipset specific method.

Typematic Rate Setting

Keystrokes repeat at a rate determined by the keyboard controller. When enabled, the typematic rate and typematic delay can be selected. The settings are: Enabled/Disabled.

Typematic Rate (Chars/Sec)

Sets the number of times a second to repeat a keystroke when you hold the key down. The settings are: 6, 8, 10, 12, 15, 20, 24, and 30.

Typematic Delay (Msec)

Sets the delay time after the key is held down before it begins to repeat the keystroke. The settings are 250, 500, 750, and 1000.

Security Option

This category allows you to limit access to the system and Setup, or just to Setup.

- | | |
|------------------------|---|
| System | The system will not boot and access to Setup will be denied if the correct password is not entered at the prompt. |
| Setup (default) | The system will boot, but access to Setup will be denied if the correct password is not entered prompt. |

OS Select For DRAM > 64MB

Allows OS2® to be used with >64MB of DRAM. Settings are Non-OS/2 (default) and OS2. Set to OS/2 if using more than 64MB and running OS/2®.

Report No FDD For Win 95

Whether report no FDD for Win 95 or not. The settings are: Yes, No.

3-6 Advanced Chipset Features

The Advanced Chipset Features Setup option is used to change the values of the chipset registers. These registers control most of the system options in the computer.

| CMOS Setup Utility - Copyright(C) 1984-2000 Award Software | | |
|---|-------------|-----------|
| Advanced Chipset Features | | |
| > Advanced DRAM Control | Press Enter | Item Help |
| > Advanced AGP Control | Press Enter | |
| DRAM Clock | PC100 SDRAM | |
| Memory Hole | Disabled | |
| System BIOS Cacheable | Enabled | |
| Video RAM Cacheable | Enabled | |
| K7 CLK_CTL Select | Default | |
| Memory Parity/ECC Check | Disabled | |
| Menu Level > | | |
| ↑ ↓ → ← Move Enter:Select Item +/-:PU/PD:Value F10:Save ESC:Exit F1:General Help F5:Previous Values F6:Optimized Defaults F7:Standard Defaults | | |

Advanced DRAM Control

Please refer to section 3-6-1

Advanced AGP Control

Please refer to section 3-6-2

DRAM Clock

This field displays the capability of the memory modules that you can use

The choice is either PC100 or PC133.

Memory Hole

You can reserve this area of system memory for ISA adapter ROM. When this area is reserved, it cannot be cached. The user information of peripherals that need to use this area of system memory usually discusses their memory requirements. The settings are: Enabled and Disabled.

System BIOS Cacheable

Selecting Enabled allows caching of the system BIOS ROM at F0000h-FFFFFh, resulting in better system performance. However, if any program writes to this memory area, a system error may result. The settings are: Enabled and Disabled.

Video RAM Cacheable

Select Enabled allows caching of the video BIOS, resulting in better system performance. However, if any program writes to this memory area, a system error may result. The settings are: Enabled and Disabled.

K7 CLK_CTL Select

This register contains values that tell the processor how to ramp up the processor ramp up the processor clock during low power modes.

The choice is either Default or Optimal.

Memory Parity

This function provides parity check of memory.

The choice is either Disabled or Enabled.

3-6-1 Advanced DRAM Control

| CMOS Setup Utility - Copyright(C) 1984-2000 Award Software | | |
|--|-----------|-----------|
| Advanced DRAM Control | | |
| | | Item Help |
| Auto Configuration | Optimized | |
| Precharge Command | 3T | |
| Active Command | 5T | |
| Active to CMD Command | 2T | |
| Write Recovery Time | 2T | |
| SDRAM Cycle Length | By SPD | |
| Bank Interleave | By SPD | |
| DRAM Drive Strength | Auto | |
| x DRAM Drive Value | 21 | |
| PCI Master Pipeline Req | Disabled | |
| P2C/C2P Concurrency | Disabled | |
| Fast R-W Turn Around | Disabled | |
| CPU to PCI Post Write | Enabled | |
| PCI Dynamic Bursting | Disabled | |
| PCI Master 0 WS Write | Disabled | |
| PCI Delay Transaction | Enabled | |
| PCI#2 Access #1 Retry | Disabled | |

↑ ↓ ←→ Move Enter:Select Item +/-/PU/PD:Value F10:Save ESC:Exit F1:General Help
F5:Previous Values F6:Optimized Defaults F7:Standard Defaults

Precharge Command

If an insufficient number of cycles is allowed for the RAS to accumulate its charge before DRAM refresh, the refresh may be incomplete and the DRAM may fail to retain date. *Fast* gives faster performance; and *Slow* gives more stable performance. This field applies only when synchronous DRAM is installed in the system. The settings are: 2 and 3.

Active Command

This field let's you insert a timing delay between the CAS and RAS strobe signals, used when DRAM is written to, read from, or refreshed. *Fast* gives faster performance; and *Slow* gives more stable performance. This field applies only when synchronous DRAM is installed in the system. The settings are: 2 and 3.

Active to CMD Command

Select the number of SCLKs for an access cycle. The settings are: 5/7 and 6/8.

SDRAM Cycle Length

When synchronous DRAM is installed, the number of clock cycles of CAS latency depends on the DRAM timing. The settings are: 2 and 3.

PCI Delay Transaction

The chipset has an embedded 32-bit posted write buffer to support delay transactions cycles. Select Enabled to support compliance with PCI specification version 2.1. The settings are: Enabled and Disabled.

3-6-2 Advanced AGP Control

| CMOS Setup Utility - Copyright(C) 1984-2000 Award Software | |
|--|---------------|
| Advanced AGP Control | |
| AGP Fast Write | Enabled |
| AGP Master 1 WS Write | Enabled |
| AGP Master 1 WS Read | Enabled |
| AGP Aperture Size | 64M |
| AGP Rate Mode | Auto |
| AGP Driving Control | Auto |
| x AGP Driving Value | DA |
| | Item Help |
| | Menu Level >> |

↑ ↓ → ← Move Enter:Select Item +/-/PU/PD:Value F10:Save ESC:Exit F1:General Help
F5:Previous Values F6:Optimized Defaults F7:Standard Defaults

Note: Change these settings only if you are familiar with the chipset.

3-7 Integrated Peripherals

| CMOS Setup Utility - Copyright(C) 1984-2000 Award Software | |
|--|--------------|
| Integrated Peripherals | |
| > OnChip IDE Function | Press Enter |
| > OnChip DEVICE Function | Press Enter |
| > OnChip SUPERIO Function | Press Enter |
| Init Display First | PCI Slot |
| | Item Help |
| | Menu Level > |

↑ ↓ → ← Move Enter:Select Item +/-/PU/PD:Value F10:Save ESC:Exit F1:General Help
F5:Previous Values F6:Optimized Defaults F7:Standard Defaults

OnChip IDE Function

Please refer to section 3-7-1

OnChip DEVICE Function

Please refer to section 3-7-2

OnChip SUPERIO Function

Please refer to section 3-7-3

Init Display First

This item allows you to decide to activate whether PCI Slot or AGP VGA first. The settings are: PCI Slot, AGP Slot.

3-7-1 OnChip IDE Function

| CMOS Setup Utility - Copyright(C) 1984-2000 Award Software | | |
|--|---------|---------------|
| OnChip IDE Function | | |
| OnChip IDE Channel0 | Enabled | Item Help |
| OnChip IDE Channel1 | Enabled | |
| IDE 32bit Transfer Mode | Enabled | |
| Primary Master PIO | Auto | Menu Level >> |
| Primary Slave PIO | Auto | |
| Secondary Master PIO | Auto | |
| Secondary Slave PIO | Auto | |
| Primary Master UDMA | Auto | |
| Primary Slave UDMA | Auto | |
| Secondary Master UDMA | Auto | |
| Secondary Slave UDMA | Auto | |
| IDE HDD Block Mode | Enabled | |
| IDE Prefetch Mode | Enabled | |

↑ ↓ → ← Move Enter:Select Item +/−/PU/PD:Value F10:Save ESC:Exit F1:General Help
F5:Previous Values F6:Optimized Defaults F7:Standard Defaults

OnChip IDE Channal0/Channel1

The integrated peripheral controller contains an IDE interface with support for two IDE channels. Select *Enabled* to activate each channel separately. The settings are: Enabled and Disabled.

Primary/Secondary Master/Slave PIO

The four IDE PIO (Programmed Input/Output) fields let you set a PIO mode (0-4) for each of the four IDE devices that the onboard IDE interface supports. Modes 0 through 4 provide successively increased performance. In Auto mode, the system automatically determines the best mode for each device. The settings are: Auto, Mode 0, Mode 1, Mode 2, Mode 3, Mode 4.


Primary/Secondary Master/Slave UDMA

Ultra DMA/100 implementation is possible only if your IDE hard drive supports it and the operating environment includes a DMA driver (Windows 95 OSR2 or a third-party IDE bus master driver). If your hard drive and your system software both support Ultra DMA 100, select Auto to enable BIOS support. The settings are: Auto, Disabled.

IDE HDD Block Mode

Block mode is also called block transfer, multiple commands, or multiple sector read/write. If your IDE hard drive supports block mode (most new drives do), select Enabled for automatic detection of the optimal number of block read/writes per sector the drive can support. The settings are: Enabled, Disabled.

3-7-2 OnChip DEVICE Function



OnChip USB

Select *Enabled* if your system contains a Universal Serial Bus (USB) controller and you have a USB peripherals. The settings are: Enabled, Disabled.

USB Keyboard Support

Select *Enabled* if your system contains a Universal Serial Bus (USB) controller and you have a USB keyboard. The settings are: Enabled, Disabled.

OnChip AUDIO Function

Please refer to section 3-7-2.1

AMR Modem DEVICE

This item allows you to decide to enable/disable the KT-133 chipset family to support AC97 Modem. The settings are: Auto, Disabled.

3-7-2.1 OnChip AUDIO Function

CMOS Setup Utility - Copyright(C) 1984-2000 Award Software
OnChip AUDIO Function

| | | |
|----------------------|----------|--|
| AC97 Sound Device | Enabled | Item Help Menu Level >> |
| Sound Blaster | Disabled | |
| SB I/O Base Address | 220H | |
| SB IRQ Select | IRQ 5 | |
| SB DMA Select | DMA 1 | |
| MPU-401 | Disabled | |
| MPU-401 I/O Address | 330-333H | |
| Game Port (200-207H) | Enabled | |

↑ ↓ → ← Move Enter:Select Item +/-/PU/PD:Value F10:Save ESC:Exit F1:General Help
 F5:Previous Values F6:Optimized Defaults F7:Standard Defaults

AC97 Sound Device

This item allows you to decide to enable/disable the KT-133 chipset family to support AC97 Audio. The settings are: Enabled, Disabled.

Game Port Address/Midi Port Address

This will determine which Address the Game Port/Midi Port will use.

3-7-3 OnChip SUPERIO Function

CMOS Setup Utility - Copyright(C) 1984-2000 Award Software
OnChip SUPERIO Function

| | | |
|------------------------|----------|--|
| Onboard FDD Controller | Enabled | Item Help Menu Level >> |
| Onboard Serial Port 1 | Auto | |
| Onboard Serial Port 2 | Auto | |
| UART 2 Mode | Standard | |
| IR Function Duplex | Half | |
| TX,RX inverting enable | No, Yes | |
| Onboard Parallel Port | 378/IRQ7 | |
| Onboard Parallel Mode | Normal | |
| ECP Mode Use DMA | 3 | |
| Parallel Port EPP Type | EPP1.9 | |

↑ ↓ → ← Move Enter:Select Item +/-/PU/PD:Value F10:Save ESC:Exit F1:General Help
 F5:Previous Values F6:Optimized Defaults F7:Standard Defaults

Onboard FDD Controller

Select Enabled if your system has a floppy disk controller (FDD) installed on the system board and you wish to use it. If you install add-on FDC or the system has no floppy drive, select Disabled in this field. The settings are: Enabled and Disabled.

Onboard Serial Port 1/Port 2

Select an address and corresponding interrupt for the first and the second serial ports. The settings are: 3F8/IRQ4, 2E8/IRQ3, 3E8/IRQ4, 2F8/IRQ3, Disabled, Auto.

UART 2 Mode

This item allows you to determine which InfraRed(IR) function of the onboard I/O chip, this functions uses.

Onboard Parallel Port

There is a built-in parallel port on the on-board Super I/O chipset that Provides Standard, ECP, and EPP features. It has the following option:

Disabled

- (3BCH/IRQ7)/ Line Printer port 0
- (278H/IRQ5)/ Line Printer port 2
- (378H/IRQ7) Line Printer port 1

Onboard Parallel Mode

- SPP : Standard Parallel Port
- EPP : Enhanced Parallel Port
- ECP : Extended Capability Port

SPP/EPP/ECP/ECP+EPP

To operate the onboard parallel port as Standard Parallel Port only, choose “SPP.” To operate the onboard parallel port in the EPP modes simultaneously, choose “EPP.” By choosing “ECP”, the onboard parallel port will operate in ECP mode only. Choosing “ECP+EPP” will allow the onboard parallel port to support both the ECP and EPP modes simultaneously. The ECP mode has to use the DMA channel, so choose the onboard parallel port with the ECP feature. After selecting it, the following message will appear: “ECP Mode Use DMA” at this time, the user can choose between DMA channels 3 to 1. The onboard parallel port is EPP Spec. compliant, so after the user chooses the onboard parallel port with the EPP function, the following message will be displayed on the screen: “EPP Mode Select.” At this time either EPP 1.7 spec. or EPP 1.9 spec. can be chosen.

3-8 Power Management Setup

The Power Management Setup allows you to configure your system to most effectively save energy saving while operating in a manner consistent with your own style of computer use.

| CMOS Setup Utility - Copyright(C) 1984-2000 Award Software | | |
|--|----------------|-----------|
| Power Management Setup | | |
| ACPI Function | Enabled | Item Help |
| > Power Management | Press Enter | |
| PM Control by APM | Yes | |
| Video Off Option | Suspend -> off | |
| Video off Method | V/H SYNC+Blank | |
| MODEM Use IRQ | 3 | |
| Soft-off by PWRBTN | Instant-off | |
| State After Power Failure | Auto | |
| > Wake-Up Events | Press Enter | |

↑ ↓ → ← Move Enter:Select Item +/-PU/PD:Value F10:Save ESC:Exit F1:General Help
F5:Previous Values F6:Optimized Defaults F7:Standard Defaults

ACPI Function

This item allows you to Enabled/Disabled the Advanced Configuration and Power Management (ACPI). The settings are Enabled and Disabled.

Power Management

Please refer to section 3-8-1

Video Off Option

This determines the manner in which the monitor is blanked. The choice are Suspend → off, All Modes → Off, and Always On.

Video Off Method

This determines the manner in which the monitor is blanked.

- | | |
|----------------|--|
| DPMS (default) | Initial display power management signaling. |
| Blank Screen | This option only writes blanks to the video buffer. |
| V/H SYNC+Blank | This selection will cause the system to turn off the vertical and horizontal synchronization ports and write blanks to the video buffer. |

Modem Use IRQ

This determines the IRQ in which the MODEM can use.

The settings are: 3, 4, 5, 7, 9, 10, 11, NA.


Soft-off by PWRBTN

Pressing the power button for more than 4 seconds forces the system to enter the Soft-Off state. The settings are: Delay 4 Sec, Instant-Off.

Wake-Up Events

Please refer to section 3-8-2

3-8-1 Power Management



Power Management

This category allows you to select the type (or degree) of power saving which is directly related to the following modes:

User Define(default) Allows you to set each mode individually. When not disabled, each of the ranges is from 1 min. to 1hr. except for HDD Power Down that ranges from 1 min. to 15 min. and disable.

Min Saving Minimum power management. Doze Mode 1H, Suspend Mode=1 hr., Power Down=15 min.

Max Saving Maximum power management. Doze Mode 1H, Suspend Mode=1 min., Power Down=1 min.

HDD Power Down

When enabled and after setting time of system inactivity, the hard disk drive will be powered down while all the other devices remain active.

The settings are: 1/2/3/4/5/6/7/8/9/10/11/12/13/14/15 Min and Disabled.

Suspend Mode

When enabled and after the set time of system inactivity, all devices except the CPU will be shut off.

The settings are: 1/2/4/8/12/20/30/40 Min, 1 Hour, and Disabled.

3-8-2 Wake up Events

CMOS Setup Utility - Copyright(C) 1984-2000 Award Software

Wake Up Events

| | | Item Help |
|----------------------------|-------------|-----------|
| VGA | OFF | |
| LPT & COM | LPT/COM | |
| HDD & FDD | ON | |
| PCI Master | OFF | |
| PowerOn by PCI Card | Disabled | |
| Wake Up On LAN/Ring | Disabled | |
| RTC Alarm Resume | Disabled | |
| x Date (of Month) | 0 | |
| x Resume Time (hh:mm:ss) | 0 : 0 : 0 | |
| Primary INTR | ON | |
| > IRQs Activity Monitoring | Press Enter | |

↑ ↓ ←→ Move Enter:Select Item +/-/PU/PD:Value F10:Save ESC:Exit F1:General Help
F5:Previous Values F6:Optimized Defaults F7:Standard Defaults

PowerOn by PCI card

This will enable the system to wake up to PCI Lan Card.

The settings are: Enabled and Disabled.

Wake Up On LAN/Ring

During Disabled, the system will ignore any incoming call from the modem. During Enabled, the system will boot up if there's an incoming call from the modem.

RTC Alarm Resume

This function is for setting date and time for your computer to boot up. During Disabled, you cannot use this function. During Enabled, choose the Date and Time Alarm:

Date(of month) Alarm

You can choose which month the system will boot up. Set to 0, to boot every day.

Time(hh:mm:ss) Alarm

You can choose what hour, minute and second the system will boot up.

Note: If you have change the setting, you must let the system boot up until it goes to the operating system, before this function will work.

IRQs Activity Monitoring

Please refer to section 3-8-2.1

3-8-2.1 IRQs Activity Monitoring

CMOS Setup Utility - Copyright(C) 1984-2000 Award Software
IRQs Activity Monitoring

| | |
|---|--|
| IRQ3 (COM 2) Enabled IRQ4 (COM 1) Enabled IRQ5 (LPT 2) Enabled IRQ6 (Floppy Disk) Enabled IRQ7 (LPT 1) Enabled IRQ8 (RTC Alarm) Disabled IRQ9 (IRQ2 Redir) Disabled IRQ10 (Reserved) Disabled IRQ11 (Reserved) Disabled IRQ12 (PS/2 Mouse) Enabled IRQ13 (Coprocessor) Disabled IRQ14 (Hard Disk) Enabled IRQ15 (Reserved) Disabled | Item Help Menu Level >>> |
| ↑ ↓ ←→ Move Enter:Select Item +/- PU/PD:Value F10:Save ESC:Exit F1:General Help F5:Previous Values F6:Optimized Defaults F7:Standard Defaults | |

3-9 PnP/PCI Configuration Setup

This section describes configuring the PCI bus system. PCI, or Personal Computer Interconnect, is a system which allows I/O devices to operate at speeds nearing the speed the CPU itself uses when communicating with its own special components. This section covers some very technical items and it is strongly recommended that only experienced users should make any changes to the default settings.

| CMOS Setup Utility - Copyright(C) 1984-2000 Award Software PnP/PCI Configurations | |
|---|-------------|
| PnP OS Installed | No |
| Reset Configuration Data | Disabled |
| Resources Controlled By | Auto (ESCD) |
| IRQ Resources | Press Enter |
| DMA Resources | Press Enter |
| PCI/VGA Palette Snoop | Disabled |
| Assign IRQ For VGA | Enabled |
| Assign IRQ For USB | Enabled |
| Item Help Menu Level > Select Yes if you are Using a Plug and Play Capable operating System Select No if You need the BIOS to Configure non-boot devices | |
| ↑ ↓ ←→ Move Enter:Select Item +/- PU/PD:Value F10:Save ESC:Exit F1:General Help F5:Previous Values F6:Optimized Defaults F7:Standard Defaults | |

Reset Configuration Data

Normally, you leave this field Disabled. Select Enabled to reset Extended System Configuration

Data (ESCD) when you exit Setup if you have installed a new add-on and the system reconfiguration has caused such a serious conflict that the operating system can not boot. The settings are: Enabled and Disabled.

Resource Controlled By

The Award Plug and Play BIOS has the capacity to automatically configure all of the boot and Plug and Play compatible devices. However, this capability means absolutely nothing unless you are using a Plug and Play operating system such as Windows®95/98. If you set this field to "manual" choose specific resources by going into each of the sub menu that follows this field (a sub menu is preceded by a ">").

The settings are: Auto(ESCD), Manual.

IRQ Resources

When resources are controlled manually, assign each system interrupt a type, depending on the type of device using the interrupt.

DMA Resources

This sub menu can let you control the DMA resource.

PCI/VGA Palette Snoop

Leave this field at *Disabled*. The settings are Enabled, Disabled.

3-10 PC Health Status

This section shows the Status of your CPU, Fan, Warning for overall system status. This is only available if there is Hardware Monitor onboard.

| CMOS Setup Utility - Copyright(C) 1984-2000 Award Software | | |
|--|----------|--------------|
| PC Health Status | | |
| Show PC Health in Post | Enabled | Item Help |
| Current CPU Temp. | 50°C | |
| Current System Temp. | 25°C | |
| Current CPUFAN1 Speed | 5000 rpm | |
| Current CPUFAN2 Speed | 5000 rpm | |
| Vcore | 1.81V | |
| Vdd | 3.45V | |
| 3.3V | 3.35V | |
| 5V | 5.10V | |
| 12V | 12.40V | |
| CPU protect for CPUFan off | Enabled | Menu Level > |

↑ ↓ ← → Move Enter:Select Item +/- PU/PD:Value F10:Save ESC:Exit F1:General Help
F5:Previous Values F6:Optimized Defaults F7:Standard Defaults

Show PC Health in Post

During Enabled, it displays information list below. The choice is either Enabled or Disabled

Current CPU Temperature/Current System Temp/Current FAN1, FAN2 Speed/Vcore/ Vdd/3.3V/+5V/+12V (V)


This will show the CPU/FAN/System voltage chart and FAN Speed.

CPU protect for CPUFan off

During Enabled, system will warn the user if CPU Fan is not functioning.

3-11 Frequency/Voltage Control

This section is for setting CPU Frequency Control.



Auto Detect DIMM/PCI Clk

This item allows you to enable/disable auto detect DIMM/PCI Clock.

The settings are: Enabled, Disabled.

CPU Host/PCI Spread Spec.

This item allows you to set the CPU Host/PCI clock and Spread Spectrum.

The choice are: Default, 100/33Mhz/-0.5%, 100/33Mhz/±0.25%, 100/33Mhz/±0.5%
102/34Mhz/Off, 104/35Mhz/Off, 106/35Mhz/Off, 107/36Mhz/Off
108/36Mhz/Off, 109/36Mhz/Off, 110/37Mhz/Off, 111/37Mhz/Off
112/37Mhz/Off, 133/33Mhz/-0.5%, 133/33Mhz/±0.25%,
133/33Mhz/±0.5%

CPU Vcore Select

This item allows you to select Vcore of the CPU. The choice are: Default, -0.025V, +0.025V, +0.05V, +0.075V, +0.1V, +0.125V, +0.15V. Max. Vcore is 1.9V.

3-12 Load Standard/Optimized Defaults

Load Standard Defaults

When you press <Enter> on this item, you get confirmation dialog box with a message similar to:

Load Standard Defaults (Y/N)? N

Pressing <Y> loads the BIOS default values for the most stable, minimal-performance system operations.

Load Optimized Defaults

When you press <Enter> on this item, you get a confirmation dialog box with a message similar to:

Load Optimized Defaults (Y/N)? N

Pressing <Y> loads the default values that are factory settings for optimal performance system operations.

3-13 Set Supervisor/User Password

You can set either supervisor or user password, or both of them. The differences are:

Supervisor password: Can enter and change the options of the setup menus.

User password: Can only enter but do not have the right to change the options of the setup menus. When you select this function, the following message will appear at the center of the screen to assist you in creating a password.

ENTER PASSWORD:

Type the password, up to eight characters in length, and press <Enter>. The password typed now will clear any previously entered password from CMOS memory. You will be asked to confirm the password. Type the password again and press <Enter>. You may also press <Esc> to abort the selection and not enter a password.

To disable a password, just press <Enter> when you are prompted to enter the password. A message will confirm that the password will be disabled. Once the password is disabled, the system will boot and you can enter Setup freely.

PASSWORD DISABLED.

When a password has been enabled, you will be prompted to enter it every time you try to enter Setup. This prevents an unauthorized person from changing any part of your system configuration.

Additionally, when a password is enabled, you can also require the BIOS to request a password every time your system is rebooted. This would prevent unauthorized use of your computer.

You determine when the password is required within the BIOS Features Setup Menu and its Security option. If the Security option is set to “System”, the password will be required both at boot and at entry to Setup. If set to “Setup”, prompting only occurs when trying to enter Setup.

第四章


驅動程式和免費軟體的安裝

在主機板的包裝內含有一片 MAGIC INSTALL 光碟片。這張光碟片包含主機板所需的

所有驅動程式和一些免費的應用軟體、工具軟體。並且，這光碟片也包含一個自動安裝程式的軟體，它能導引你進行驅動程式的安裝，以及何種驅動程式需要安裝，從而簡化安裝步驟，該安裝程式軟體就是本公司自行開發完成的 MAGIC INSTALL。

支援 WINDOWS 95/98/98SE/NT4.0/2000 的 MAGIC INSTALL

把光碟片插入光碟機，然後將出現 MAGIC INSTALL 主畫面。如果沒有出現此畫面，請按下“我的電腦”然後選擇光碟機，或者在“開始”的目錄選擇“執行”，輸入“X:\SETUP.EXE”(假設你的光碟機路徑是 X :)



在 MAGIC INSTALL 主畫面有 6 項選擇：

1. IDE 安裝 VIA 四合一驅動程式
2. PC-HEALTH 安裝 VIA 的硬體監控程式
3. SOUND 安裝 AC'97 音效裝置的驅動程式
4. PC-CILLIN 安裝 PC-CILLIN98 防病毒驅動程式
5. BROWSE CD 瀏覽 CD 內容
6. EXIT 退出 MAGIC INSTALL 目錄

4-1 IDE

安裝 VIA 四合一驅動程式


IDE : 安裝 VIA 所提供的 ATAPI 驅動程式，用於處理 IDE 裝置的相容性問題。

AGPVXD : 安裝 VIA 的 AGPVXD 驅動程式。如果你使用 AGP 類型的顯示卡，VIAGART.VXD 可以直接支援 VGA 卡驅動程式的服務程序及介面至硬體


裝置，以提供更快速的圖形存取。

IRQ ROUTING : 安裝 VIA 的 PCI IRQ MINIPORT 驅動程式 (只支援 Windows 98)。它可修正 PCI 中斷裝置之路線安排順序。

INF : 安裝 VIA 在 Windows 下的註冊程式。此一驅動程式可用來啟動 VIA 的電源管理控制裝置。



1. 在 MAGIC INSTALL 介面單擊 IDE 這個選項



3. 在版權說明出現後，單擊 NEXT



5. 單擊 NEXT，即可安裝製造商所提供的
ATAPI 驅動程式



6. 單擊 NEXT，選取啟動 DMA 模式



7. 單擊 NEXT，即可安裝 VIA 的 AGP VXD
驅動程式

8. 單擊 NEXT，即可安裝 VIA 的 IRQ
Routing Mini port 驅動程式




9. 單擊 Finish 即可重新啟動系統

4-2 PC-HEALTH 安裝 VIA 的硬體監控程式




- 在 MAGIC INSTALL 畫面單擊 PC - HEALTH



- 當 VIA 的硬體監控程式安裝精靈出現時，單擊 NEXT





- 單擊 Next，即可將驅動程式安裝至 C:\VIAHM 的路徑



- 單擊 Next，選用預定的檔案夾名稱

4-2-1 如何使用 VIA 的硬體監控程式



- 選取 Programs \VIA HM，即可出現如右的畫面

4-3 Sound VIA AC'97 音效裝置的驅動程式



1. 在 MAGIC INSTALL 畫面單擊 SOUND 的選項



2. 當 VIA 音效驅動程式的安裝精靈出現時，單擊 Next




3. 單擊 Next，開始安裝 VIA 的音效驅動程式



4. 所有的檔案拷貝完成後，請單擊 Finish 完成拷貝程序



5. 系統會自動偵測並拷貝所需的驅動程式



6. 大約 10~20 秒後，系統就會自動開始安裝遊戲埠和搖桿的驅動程式

4-4 PC-CILLIN 安裝 PC-CILLIN98 防病毒程式




- 在 MAGIC INSTALL 畫面單擊 PC-CILLIN 的選項




- 當“PC-CILLIN 98 OEM SETUP”視窗出現後，單擊“NEXT”，即可出現版權說明，單擊“YES”，軟體就開始檢查硬碟




- 單擊“NEXT”或選“BROWSE”改變安裝路徑。



- 完成安裝後，選擇 YES 或 NO，確定是否要將 PC-CILLIN 加到 ACTIVE CHANNEL 或你的網際網路瀏覽器。



- 如果你想製造一片緊急修復磁碟片，請將空白磁碟片插入 1.44MB 軟碟機



- 單擊“Finish”，重新啟動系統

4-5 如何關閉內建式音效卡

進入 BIOS SETUP 程式，選擇 INTEGRATE PERIPHERALS，選擇 ON-CHIP DEVICE

FUNCTION，選擇 AC97 AUDIO，按 PAGE DOWN 鍵選擇 Disable，即可關閉主機板上的音效裝置。

4-6 怎樣更新 BIOS

- 第一步.** 準備一張啟動磁片 (你可以在“開始/執行”中輸入“SYS A:” , 單擊“確定”)。
- 第二步.** 將工具軟體複製到啟動磁片，可以將光碟片的 X:\FLASH\AWDFLASH.EXE 複製到磁碟片，或從我們的網頁下載。
- 第三步.** 從我們的網頁下載最新的 663AS PRO BIOS，並複製到啟動磁片。
- 第四步.** 插入啟動磁片到 A 磁碟槽，啟動系統，看到“A :”的提示後，輸入“Awdflash A:\663ASPROxxx.BIN /SN/PY/CC/R”指令，663ASPROxxx.BIN 代表最新版本的 BIOS，它類似 663ASPROA03.BIN 或 663ASPROB02.BIN。
 - SN 表示 不保存現在的 BIOS 數據
 - PY 表示 更新 BIOS 數據
 - CC 表示 清除 CMOS 數據
 - R 表示 重新啟動系統
- 第五步.** 按 ENTER 鍵，等 BIOS 被重新更新後，系統即自動重新啟動。