

Presario 7100

System Boards (w/o Processor)	Spare Part	System
486 System Board English, French, Spanish	188826-001	7110
586 System Board, P54C, English, French, Spanish	188827-001	7150,7152, 7170, 7180
486 System Board, German, Dutch, Italian	188987-001	7104, 7106, 7110
586 System Board, P54C, German, Dutch, Italian	188988-001	7150,7152, 7170, 7180

Processor Jumper Settings, 486 Boards w/ 8 MB

	AMD 486 DX2/80	AMD 486 DX2/80 PLUS	AMD 486 DX4/100	AMD 486 DX4/100 PLUS	CYRIX 486 DX2 V80	INTEL P24T
JC1	OPEN	2 - 3	OPEN	2 - 3	1 - 2	OPEN
JC2	OPEN	2 - 3	OPEN	2 - 3	1 - 2	2 - 3
JC3	OPEN	2 - 3	OPEN	2 - 3	1 - 2	OPEN
JC4	OPEN	2 - 3	OPEN	2 - 3	1 - 2	2 - 3
JC5	OPEN	2 - 3	OPEN	2 - 3	1 - 2	OPEN
JC6	OPEN	2 - 3	OPEN	2 - 3	1 - 2	OPEN
JC7	OPEN	2 - 3	OPEN	2 - 3	1 - 2	2 - 3
JC8	OPEN	2 - 3	OPEN	OPEN	OPEN	OPEN
JC9	2 - 3	1 - 2	2 - 3	1 - 2	1 - 2	3 - 4
JC10	1 - 2	2 - 3	OPEN	2 - 3	OPEN	OPEN
JC11	2 - 3	2 - 3	2 - 3	2 - 3	2 - 3	1 - 2
JP16	3 - 4	3 - 4	3 - 4	3 - 4	1 - 2	5 - 6, 7 - 8, 9 - 10
JP26	OPEN	OPEN	1 - 2	1 - 2	OPEN	1 - 2

Configuration Jumper Settings, 486 boards W/8 MB (R02*, R03*)

Jumper	Function	Setting	Description
JP7	Manually clear RTC and CMOS	1 - 2 2 - 3 (default)	CMOS Discharged Normal

* Board Revision Level 2 (R02) and Revision Level 3 (R03).

Configuration Jumpers for 586 Models (R02*, R03*)

Jumper	Function	Setting	Description
JP4	Sound Subsystem	Open (default) Closed	ES1688 Enabled ES1688 Disabled
JP7	CPU core/bus select	1 - 2 3 - 4 (default) 1 - 2, 5 - 6	75/50 MHz 90/60 MHz 100/66.6 MHz
JP201	Manually clear RTC and CMOS	1 - 2 2 - 3 (default)	CMOS Discharged Normal

* Board Revision Level 2 (R02) and Revision Level 3 (R03).

Microprocessors	Spare Part	System
486DX2/80	188816-001	7104, 7106
486SX4/100	188817-001	7104, 7106, 7110
P54C/75	188818-001	7150, 7152
P54C/90	188819-001	7170
P54C/100	188843-001	7180

Presario 7100

Memory	Spare Part	System
4 MB SIMM, 70ns, Tin/Lead Contacts	188807-001	Note 1, 2
8 MB SIMM, 70ns, Tin/Lead Contacts	188808-001	Note 1
128K Cache Memory	188809-001	Note 1
256K Cache Memory	188810-001	Note 2
Video Memory, 512 KB	188976-001	Note 1
Video Memory, 1 MB	188811-001	Note 1, 2

¹ 486 models.

² 586 models only.

Hard Drives	Spare Part	System
420 MB	188801-301	Note 1, 2
540 MB	188802-301	Note 1, 2
840 MB	188803-301	Note 1, 2
1.275 GB	188999-001	Note 1, 2

¹ 486 Models.

² 586 Models.

CD-ROM Drive	Spare Part
CD-ROM, IDE, 4-spd	188842-301

Diskette Drives	Spare Part
1.44 MB, 3.5"	188800-301

Miscellaneous	Spare Part
Riser Board	188820-001
Microphone	188837-301
Speaker, w/ Cable	188825-301
Keyboard, U.S.	188838-301

14.4K bps FAX Modem, TAM, Speakerphone

Country	Spare Part
U.S., Latin America, Canada, French Canadian	188812-001
Germany	188813-041
Netherlands	188813-331
United Kingdom	188813-031
Japan	188813-191

Cable Information	Spare Part
Cables: FDD, HD, CD, Aud, Mod, Game, LEDs, Serial Ports	188840-001
Cables, 4, External RJ-11 Modem (U.S./North America, Japan, Germany, United Kingdom)	188985-001

ROM Information	Spare Part
ROM, BIOS 1, 486, English, French, Spanish	188821-001
ROM, BIOS 2, 486, German, Dutch, Italian	188822-001
ROM, BIOS 1, 586, English, French, Spanish	188823-001
ROM, BIOS 2, 586, German, Dutch, Italian	188824-001

Presario 7100

Power Supply/Battery	Spare Part
Power Supply	188814-001
Power Supply, Europe Only	188815-001
Real-Time Clock Battery	188929-001

NO MEMORY UPGRADE CHART

COMPAQ MEMORY OPTIONS NOT CURRENTLY OFFERED

NOTE: Memory is expandable up to 128 MB with 70ns tin-lead FAST-PAGE memory modules. Must add modules in matched pairs.