



"Welcome to Daewoo Telecom."
 "For product inquiries: Toll free number: 080-022-8383"
 "Land number: 02-319-3660~5"
 "Daewoo Telecom strives to provide the best products and services to consumers."

Q1. Get CPC-2900 main B/D information with Winpro .

>
 > My friend replaced the main B/D of his CPC-2900 and received the remaining board.
 > Lost the user manual of the main board, and the speaker, Reset, HDD-Lamp, ClockSpeed, etc.
 > Looking for Pin, DipS/W information.
 >
 > We would really appreciate it if you could fax us a copy of the manual.
 > Fax: 0546) 461-7337, Reference (Tel: 0546-467-5532)
 >
 > Or, if there is information describing the function of Pin and DipS/W
 > Thank you for sending it.
 >
 > If both of the above methods are difficult, I appreciate any advice on other methods.

A1. * CPC-2900


1. PLUG & PLAY READY SYSTEM
 - When improving the system by installing sound, multimedia, network cards, etc. Automatically set the memory area using the system's IRQ, DMA, and I/O
2. VESA MODE 3 function support
 - By turning on the VESA MODE 3 function, the data transfer speed of the HDD is significantly improved. The data transfer rate is further increased by
3. Apply FLASH ROM
4. VESA LOCAL WINDOWS ACCELERATE VGA CARD
5. Using low-noise and high-efficiency SMPS
6. GREEN function

yu tong dragon weave board dragon	
Model	2900 2900G 2900 2900 2900G 2900G
	G TS382 TX585 G TX685 G WS382 WX585 WX685
CPU	486SX33 486DX250 486DX266 486SX33 486DX250 486DX266
CPU Socket	237-Pin Pentium Overdrive Socket
Internal	8 KB
Kesh	
External	- 128KB 128KB
Memory	4 MB, 72-pin memory module
	3.5 1 (Drive B) 1 (Drive B)
FDD	
	5.25 1 (drive A) 1 (drive A)
HDD	270MB 540MB 270MB 540MB
VIDEO	Daewoo CPA-209 (S/W Korean Font) Daewoo CPA-210 (H/W Korean Font)
Expansion slots	VESA : 2, 16-BIT ISA : 4
Mouse	PS/2 Style Mouse
Keyboard	Korean/English 103 Key Keyboard
I/O	Serial communication port: 2 (9-pin, 25-pin), parallel communication port: 1 (25-pin)
Others	- VESA local high-speed hard disk support, low-noise power supply Meets the standards of the US Environmental Protection Agency (EPA)
Basic	- Korean MS-DOS 6.X
S/W	- Korean WINDOWS 3.X
	- Pro notebook

* CACHE MEMORY


CACHE SRAM	
CACHE SIZE	TAG SRAM U20
U11 - U14	U16 - U19
64KB	8K X 8BIT 8K X 8BIT 8K X 8BIT
128KB	32K X 8BIT 32K X 8BIT
256KB	32K X 8BIT 32K X 8BIT 32K X 8BIT

* SIMM MEMORY



BANK 0	BANK 1	Total memory
4M	-	4M
4M	4M	8M
8M	-	8M
8M	4M	12M
8M	8M	16M
16M	-	16M
16M	4M	20M
16M	8M	24M
16M	16M	32M
32M	-	32M
32M	4M	36M
32M	8M	40M
32M	16M	48M
32M	32M	64M

* JUMPER & SWITCH SETTINGS



* JUMPER SETTING

PIN NO	DESCRIPTIONS	BRIDGED
JP4	CMOS CLEAR OR NOT	1-2 : NORMAL (default) 2-3 : CMOS RAM CLEAR
JP5	CPU TYPE	1-2 & 3-4 : SX2/DX/DX2/OVERDRIVE 2-3 : SX ONLY
JP6	LOCAL IDE	BRIDGED : ENABLE (default) OPEN : DISABLE
JP7	CPU SPEED	BRIDGED : > 33MHz in VL-BUS OPEN : = 33MHz
JP8	CPU SPEED SELECTION	1-2 & 3-4 : OFF & OFF : 25MHz 1-2 & 3-4 : ON & ON : 33MHz
J4	EXTERNAL BATTERY CONNECTOR	
J7	TURBO & POWER & HDD LED & RESET CONNECTOR	
J8	SPEAKER CONNECTOR	
J17	DPMS CONNECTOR	
SW1	CACHE SIZE	64K 128K 256K
DIP SWITCH 1,2,3,4 OFF 2,4 ON 1,2,3 ON		

Daewoo Telecom supports Microsoft's Internet Explorer and Netscape's Netscape at the same time. 