



s661FXm-FSN



- DieHard BIOS Lite
- Onboard AC'97 CODEC
- Front Audio Connector
- S/PDIF Connector
- AUX_IN Connector
- CD_IN Connector
- STBY LED
- AGP LED
- 32-bit PCI Expansion Slots x3
- USB 2.0 Connector x 2
- IEEE 1394 Connector
- Serial ATA Ports x2
Supports 150 MB/s Transfer Rate
- Front Panel Connector
- JP14 CMOS Data Clear Jumper
- SYSFAN2 Connector

- Realtek 10/100 LAN Chip
- JP28 PS2 KB/Mouse Wakeup Jumper
- 4-pin 12V ATX Power Connector
- JP2, JP3 CPU FSB Jumper
- SYSFAN1 Connector
- AGP 8X Expansion Slot that supports 8X AGP card(2.1GB/s)
- 479-pin CPU socket with Voltage and Frequency Auto-detection that supports Intel® Pentium® M (Dothan and Banias) and Celeron® M CPU
- SIS® 661FX/964 Chipsets that support 400/533 MHz FSB
- CPUFAN Connector
- 184-pin DIMMsx2 support DDR400/333/266 Max. To 2GB
- IDE Connectors x 2 (ATA 66/100/133 supported)
- ATX Power Connector
- IrDA Connector
- FDD Connector

AOpen reserves the right to revise all the specifications and information contained in this document, which are subject to change without notice.




Before You Start

Everything you need to boot this motherboard is included in this Easy Installation Guide. For more information, a complete **Online User's Manual** can be found in the **Bonus Pack CD**. Thanks for the help of saving our earth.

Accessory Checklist

- Easy Installation Guide x 1
- Enhanced Full Pictured Manual x 1
- 80-Wire IDE Cable x 1
- Floppy Drive Cable x 1
- Serial ATA Cable x 1
- Serial ATA Power Cable x 1
- Back Panel I/O Shield x 1
- Bonus Pack CD x 1
- CPU Cooler x 1

Installing By Yourself




PART NO: 49.8EM0E.EE10

DOC. NO: S661FXMFSN-EG-E0602A

1. Installing CPU

This socket supports uFCPGA package CPU, which is the latest CPU package developed by Intel. Other forms of CPU package are impossible to be fitted in.




1. Unscrew socket screw counter-clockwise.
2. Locate Pin 1 in the socket and look for a golden arrow on the CPU upper interface. Match Pin 1 and golden arrow. Then insert the CPU into the socket.
3. Lock the socket screw clockwise to fasten CPU.

Note: If you do not match the CPU socket Pin 1 and CPU golden arrow well, you may damage the CPU.

2. Installing CPU & System Fans


Plug in the CPU fan cable to the 3-pin CPUFAN connector. If you have chassis fan, you can also plug it in SYSFAN1 or SYSFAN2 connector.



Note: Some CPU fans do not have sensor pin so they cannot support fan monitoring.

3. Installing Memory Modules


DIMM slots are designed in black which are very easy to recognize. Insert the module straight down to the DIMM slot with both hands and press down firmly until the DIMM module is securely in place.



Note: The tabs of the DIMM slot will close-up to hold the DIMM in place when the DIMM touches the slot's bottom.

4. Connecting IDE and Floppy Cables

Connect 34-pin floppy cable and 40-pin, 80-wire IDE cable to floppy connector FDD and IDE connector. Be careful of the pin1 orientation. Wrong orientation may cause system damage.



ATA 66/100/133 IDE Connector

FDD Connector


5. Connecting Front Panel cable

Attach the power LED, speaker, and reset switch connectors to the corresponding pins. If you enable "Suspend Mode" item in BIOS Setup, the ACPI & Power LED will keep flashing while the system is in suspend mode.

Locate the power switch cable from your ATX housing. It is 2-pin female connector from the housing front panel. Plug this connector to the soft-power switch connector marked *SPWR*.


1	NC		Power Switch
	NC		GND
	+5V		Power LED-
	HDD LED		GND
	HDD LED		Power LED+
	+5V		NC
	+5V		GND
	GND		GND
	NC		RESET
	SPEAKER		GND

Front Panel Connector



6. Connecting ATX Power Cables


This motherboard comes with a 24-pin and 4-pin ATX power connector as shown below. Make sure you plug in the right direction. We strongly recommend you to insert the 4-pin connector before connecting the 24-pin connector.



7. Power-on and Loading BIOS Setup


Del

After you finish the setting of jumpers and connect correct cables. Power on and enter the BIOS Setup, press during POST (Power On Self Test). Choose "Load Setup Defaults" for recommended optimal performance.



8. AOpen EzInstall and Bonus Pack CD

You can use the autorun menu of Bonus CD disc. Choose the utility and driver from the icons at left side, and then click on the "GO" button to complete installation automatically.



Setting CPU Voltage & Frequency

Setting CPU Core Voltage

This motherboard supports Voltage ID (VID) function to detect CPU voltage automatically during power-on.

Setting CPU Frequency

This motherboard is CPU jumper-less design, you can set CPU frequency through 1MHz stepping CPU Overclocking in the BIOS. CPU Core Frequency = CPU FSB clock x CPU Ratio. However, all CPU now selling in the market belong to "Fixed Multiplier". That means users can not adjust the CPU Ratio but only change CPU FSB clock to achieve overclocking.

(Users do the overclocking at their own risk!!)

BIOS Setup > Frequency / Voltage Control > CPU Bus Frequency

CPU Ratio	4x, 5x... 17x, 18x, 20x
CPU FSB (Adjustment manually)	FSB = 100MHz - 400MHz by 1MHz Stepping CPU Overclocking

Processor Number	Architecture	Clock Speed	Front Side Bus	Cache	Ratio
Pentium M 770	90nm	2.13GHz	533MHz	2MB L2	16x
Pentium M 760	90nm	2.00GHz	533MHz	2MB L2	15x
Pentium M 750	90nm	1.86GHz	533MHz	2MB L2	14x
Pentium M 740	90nm	1.73GHz	533MHz	2MB L2	13x
Pentium M 730	90nm	1.60GHz	533MHz	2MB L2	12x
Pentium M 765	90nm	2.10GHz	400MHz	2MB L2	21x
Pentium M 755	90nm	2.00GHz	400MHz	2MB L2	20x
Pentium M 745	90nm	1.80GHz	400MHz	2MB L2	18x
Pentium M 735	90nm	1.70GHz	400MHz	2MB L2	17x
Pentium M 725	90nm	1.60GHz	400MHz	2MB L2	16x
Pentium M 715	90nm	1.50GHz	400MHz	2MB L2	15x
Pentium M 705	130nm	1.50GHz	400MHz	1MB L2	15x
Celeron M 370	90nm	1.50GHz	400MHz	1MB L2	15x
Celeron M 360	90nm	1.40GHz	400MHz	1MB L2	14x
Celeron M 350	90nm	1.30GHz	400MHz	1MB L2	13x
Celeron M 340	130nm	1.50GHz	400MHz	512KB L2	15x
Celeron M 330	130nm	1.40GHz	400MHz	512KB L2	15x

Note: With CPU speed changing rapidly, there might be faster CPU on the market by the time you received this installation guide. This table is kindly for your references only.



Tip: When you fail to overclock, you could:

1. Clear CMOS (JP14) to restore the default setting.
2. After turning power on, press "Home" immediately until the screen appears.





Warning: SiS 661FX chipset support maximum 533MHz (133MHz*4) system bus; higher clock setting may cause serious system damage.

JP14 Clear CMOS

You can clear CMOS to restore system default setting. To clear the CMOS, follow the procedure below.

1. Turn off the system and unplug the AC power.
2. Remove ATX power cable from connector PWR2.
3. Locate JP14 and short pins 2-3 for a few seconds.
4. Return JP14 to its normal setting by shorting pin 1 & pin 2.
5. Connect ATX power cable back to connector PWR2.





Tip: When should I Clear CMOS?

1. Boot fails because of overclocking...
2. Forget password...
3. Troubleshooting...


JP28 Keyboard/Mouse Wakeup Jumper

This motherboard provides keyboard / mouse wake-up function. You can use JP28 to enable or disable this function, which could resume your system from suspend mode with keyboard or mouse. The factory default setting is "Disable" (1-2), and you may enable this function by setting the jumper to 2-3.




IEEE 1394 Connectors

With IEEE1394 Chip on board (AGERE 1394), having its data transfer rate up to 400Mb/s, this interface can connect to devices that require high data transferring performance such as digital camera, scanner or others IEEE 1394 devices. Please use appropriate cables to connect IEEE1394 devices.




Front Audio Connectors

If the housing has been designed with an audio port on the front panel, you'll be able to connect onboard audio to front panel through this connector. By the way, please remove 5-6 and 9-10 jumper caps from the Front Audio Connector before connecting the cable. Please do not remove these 5-6 and 9-10 yellow jumper caps if there's no audio port on the front panel.




Dual Gigabit LAN onboard

On the strength of SIS 10/100 LAN controller on board, this motherboard provides 10/100Mbps Ethernet for office and home use. The Ethernet RJ45 connector is located on the top of USB connectors. The right hand side LED indicates link mode; it lights in yellow when linking to network. The left hand side LED indicates the transfer mode and will light in green when data is transferring at 100Mbps (never lights while at 10Mbps). To enable or disable this function, you may simply adjust it through BIOS. To enable LAN wakeup function, you have to set the "Wake on PCI Card" enable in the BIOS "Power Management Setup" section.



Serial ATA Connectors


To connect a serial ATA disk, you have to have a 7-pin serial ATA cable. Connect two ends of the serial ATA cable to the serial ATA header on the motherboard and the disk. Like every other traditional disk, you also have to connect a power cable. Please be noted that it is a jumper free implement; you don't need to set jumpers to define a master or slave disk. When serial ATA hard disks are installed on serial ATA ports, the one connected on SATA1 will be set as the first boot device automatically. **Please note that it doesn't support Hot-Plug in function.**





Troubleshooting


If you encounter any trouble to boot your system, follow the procedures accordingly to resolve the problem.



*1 The VGA card is not necessary to be installed if your monitor is connected to the onboard VGA port.
 *2 If you connect to the onboard VGA port and no screen displays, then your onboard VGA device might have problem.

Model name and BIOS version


Model name and BIOS version can be found on upper left corner of first boot screen (POST screen). For example:



s661FXm-FSN is model name of motherboard; R1.02 is BIOS version

Register Your Motherboard

Thanks for choosing AOpen product, please register this motherboard at <http://club.aopen.com.tw/productreg/> to become a Gold member of Club AOpen, and to ensure high service quality and priority from AOpen. You will also have a chance to play slot machine game to win prize from AOpen. Please prepare the following information before you start: **Model Name, Part Number (P/N), Serial Number (S/N) and Purchase Date.** The Part Number and Serial number are printed on bar code label. You can find this bar code label on the outside packing or on component side of PCB. For example:



P/N: 91.88110.201 is part number, S/N: 91949378KN73 is serial number.

Phoenix-Award BIOS ERROR Message	
Beep Sound	Message
1 short(Beep)	System booting is normally.
1 long - 1 short(Beep)	DRAM ERROR
1 long - 2 short(Beep)	Display card or monitor connected error
1 long - 3 short(Beep)	Keyboard Error
Long(Beep) continuous	DRAM hasn't inset correctly.




Technical Support

Dear Customer,

Thanks for choosing AOpen products. We invite you to register at <http://www.aopen.com> to become a Gold Member of Club AOpen so as to ensure quality service in the future. In order to maintain the best service to every customer of us, we recommend you to follow the procedures below and seek help from our branches according to the region you buy the product. With your help, we can then continue to provide efficient and the best quality service to every customer.

Thanks very much for your understanding!



Europe: <http://www.aopen.nl/tech/default.htm>
Pacific Rim: <http://www.aopen.com.tw/tech/default.htm>
China: <http://www.aopen.com.cn/tech/default.htm>
Germany: <http://www.aopencom.de/tech/default.htm>
America: <http://usa.aopen.com/tech/default.htm>
Japan: <http://aopen.jp/tech/index.html>

Online Manual: To download manual, please log on and then select your preferred language. Under "Type" directory, choose "Manuals" to go to our manual database. You can also find the manual and EIG in AOpen Bonus Pack.
<http://download.aopen.com.tw/>

Test Report: We recommend you to choose board/card/device from the compatibility test reports for assembling your PC. It may prevent incompatibility problems.
<http://global.aopen.com.tw/tech/report/default.htm>

FAQ: Here we list problems that users often encounter and FAQ (Frequently Asked Questions). You may select your preferred language after log on, and may be able to find a solution to your problem.
<http://club.aopen.com.tw/faq/>

Download Software: After log on and having language selected, you may get the latest updated BIOS/utility and drivers you need under "Type" directory. In most case, newer versions of drivers and BIOS have solved earlier bugs or compatibility problems.
<http://download.aopen.com.tw/>

eForum: AOpen eForum is provided to discuss our products with other users, in which your problem probably had been discussed before or will be answered. After log on, you may select your preferred language under "Multi-language".
<http://club.aopen.com.tw/forum>

Contact Us: Please prepare detail system configuration and error symptom before contacting us. The part number, serial number and BIOS version are also very helpful.

Contact Distributors/Resellers: We sell our products through resellers and integrators. They should know your system configuration very well and should be able to solve your problem efficiently and provide important reference for you.