



Packard Bell 286B M/Board

[Home](#)
[What's New](#)
[Contact Us](#)

Search the Site

Find

powered by
[FreeFind](#)

[Acer](#)
[Advent](#)
[Amstrad](#)
[Apple](#)
[Canon](#)
[Compaq](#)
[CTX](#)
[Epson](#)
[Hewlett Packard](#)
[Mitsubishi/Apricot](#)
[Packard Bell](#)
[Other Manufact.](#)

[File Extensions](#)
[Humour](#)
[Links](#)
[Microsoft](#)
[Reference](#)
[Scanner Support](#)

Specification

- **Battery** : Removable , not rechargeable
- **BIOS** : 2 X 32Kb - Phoenix BIOS 2 X 8-bit ISA Phoenix 3.07. To access - Run setup.exe
- **Cache** : N/A
- **Clock/Driver** : (RTC)
- **Cover Removal** : 5 screws
- **CPU** : 80286-10 MHz Keyboard Switchable (Ctrl)-(Shift)-(NumLock) toggles between 8 MHZ and 10 MHz 80287-8 (optional)
- **Drive Cavities** : 2 X half-height (exposed), 1 X half-height (enclosed)
- **I/O Expansion slots** : 6 x 16-bit ISA, 2 x 8-bit ISA
- **Interfaces** :
 - 1 DB-25 Parallel Port
 - 1 RS-232C, DB-9 Serial Port
 - 1 5-pin DIN Keyboard Port
 - 1 PS/2 Mouse Port
 - 1 15-pin VGA Port
 - 1 15-pin Game Port
- **Power Supply** : 200 watts
- **RAM** : Standard on motherboard: 640Kb, Maximum on motherboard : 1MB (use 64Kb, 256Kb DRAMs, 150ns)
- **Speaker** : Internal - cone on chassis
- **Video** : PB-EGA or PB-EGA/RS on Card.

Jumpers

Jumper	Function	Pins	Description
JP1	Display Type	OPEN CLOSED	Monochrome * Colour
JPF	Floppy Controller	OPEN CLOSED	Enabled * Disabled

* Default

Upgrades

- **Cache Memory** : This system does not support cache memory.
 - **Maths Co-Processor** : An 80287-8 co-processor can be installed in socket U33, no jumpers need to be changed.
 - **RAM** : Standard on motherboard: 640Kb, Maximum on motherboard : 1MB (use 64Kb, 256Kb DRAMs, 150ns)
 - **Video Memory** : This system has a video card, upgrade depends on card.
-
-