

* Å¬, &hibar;Çİ, é Å©°Ö °¼ ¼ö ÅÖ½Ä Ĩ'Ù.



°ü·Ã Á²°, °,±â
CPU Á²°
CMOS SETUP
.P, ð, ® Á²°
Ä,ÆÛ ¼³Ä²
Board History

 °, µâ »ç³/ç

‚pÄÄ Ĩ¼Ä	Intel FW82815
È®Äâ ½½ Ö	AGP - 1³, PCI - 3³
CPU Áöçø	Intel Socket-370 (370pin PGA Socket)
‚ÄÄ-Ä® solution	168 pin SDRAM 100/133MHz Áöçø
On Board	SOUND (CS 4281), VIDEO (Intel i815)
çÛ Çü	238mm * 238mm * 1.6t (4 Layers) : Micro ATX form factor



점퍼 번호	설정		기능
	1-2 (기본 설정)	2-3	
J1	Enable	Disable	PCI Audio 사용 기능
J3	Enable	Disable	CMOS Setup 저장 기능
J4	Disable	Enable	CMOS Clear
J5	Enable	Disable	Pass word 사용 기능
J6	Disable	Enable	FDD 쓰기 금지 기능



프로세서 타입	지원 가능 프로세서
Intel Socket-370 (370pin PPGA Socket)	Intel Celeron 400/433/466/500MHz 66MHZ Host clock Intel Coppermine 500/550/600MHz 100MHZ Host clock Intel Coppermine 667/733/933MHz 133MHZ Host clock



규격	타입	소켓	최대 확장
3.3V SDRAM (168pin)	SDRAM 100/133MHz	168Pin 3.3V 소켓 2개	512MB

DIMM Size	Non-ECC	DIMM Size	Non-ECC
8MB	4 * (1M * 16bit)	64MB	8 * (8M * 8bit)
16MB	8 * (2M * 8bit)	64MB	4 * (8M * 16bit)
32MB	4 * (4M * 16bit)	128MB	8 * (16M * 8bit)
32MB	2 * (4M * 32bit)		



BIOS Setup Utility					
Main	Advanced	Security	Power	Boot	Exit
System Time : [10:42:37] System Date : [02/06/2001] Legacy Diskette A : [1.44/1.25 MB 3 1/2] Legacy Diskette B : [Disabled] <input type="checkbox"/> Primary Master [XXXX XXXX] <input type="checkbox"/> Primary Slave [None] <input type="checkbox"/> Secondary Master [XXX XXX XXX] <input type="checkbox"/> Secondary Slave [None] System Memory : 640 KB Extended Memory : XXXXX KB Cache Ram XXX KB BIOS Version 1.01				Item Specific Help <Tab>, <Shift - Tab>, or <Enter>, selects field.	
F1	Help	상하 화살표	Select Item	-/+	Change Values
ESC	Exit	좌우 화살표	Select Menu	Enter	Select <input type="checkbox"/> Sub-Menu
F9	Setup Defaults			F10	Save and Exit