


DTK COMPUTER, INC.

PTM - 1000 (V1)

Processor 80286
Processor Speed 10MHz
Chip Set None
Max. Onboard DRAM 1MB
Cache None
BIOS DTK
Dimensions 333mm x 222mm
I/O Options None
NPU Options 80287



CONNECTIONS			
Purpose	Location	Purpose	Location
Speaker	J17	Turbo switch	J23
Power LED & keylock	J19	External battery	J24
Turbo LED	J21	Reset switch	SW2

Continued on next page . . .

DTK COMPUTER, INC.
PTM - 1000 (V1)

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper	Position
í Monitor type select color	J2	pins 1 & 2 closed
Monitor type select monochrome	J2	pins 2 & 3 closed
í DRAM speed select 0 wait states	J25	Open
DRAM speed select 1 wait state	J25	Closed
í Base memory size select 512KB	J26	pins 1 & 2 closed
Base memory size select 640KB	J26	pins 2 & 3 closed
Note: Base memory size select jumper (J26) is only functional when 1MB of DRAM is installed.		

DRAM CONFIGURATION		
Size	Bank 0	Bank 1
512KB	(18) 41256	NONE
640KB	(18) 41256	(18) 4164
1MB	(18) 41256	(18) 41256

DRAM JUMPER CONFIGURATION	
Size	J18
512KB	pins 2 & 3 closed
640KB	pins 1 & 2 closed
1MB	pins 2 & 3 closed

BIOS CONFIGURATION				
Size	SW1/1	SW1/2	SW1/3	SW1/4
27128	On	On	Off	Off
27256	Off	Off	On	On