


UNIDENTIFIED

HT 12 286

Processor 80286
Processor Speed 12/16MHz
Chip Set Headland
Max. Onboard DRAM 4MB
Cache None
BIOS AMI
Dimensions 220mm x 220mm
I/O Options None
NPU Options 80287



CONNECTIONS			
Purpose	Location	Purpose	Location
Turbo switch	JP2	Speaker	JP5
Turbo LED	JP3	Power LED & keylock	JP6
Reset switch	JP4	External battery	JP10

Continued on next page . . .

UNIDENTIFIED

HT 12 286

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper	Position
í Factory configured - do not alter	JP1	N/A
í BIOS type select 27512	JP7	pins 1 & 2 closed
BIOS type select 27256	JP7	pins 2 & 3 closed
í NPU mode select synchronous with CPU	JP8	pins 2 & 3 closed
NPU mode select synchronous with oscillator installed at Y1	JP8	pins 1 & 2 closed
í NPU speed select source/1	JP9	pins 1 & 2 closed
NPU speed select source/3	JP9	pins 2 & 3 closed
í CPU speed select 16MHz	JP11	pins 2 & 3 closed
CPU speed select 12MHz	JP11	pins 1 & 2 closed
í Monitor type select color	JP12	Closed
Monitor type select monochrome	JP12	Open

DRAM CONFIGURATION						
Size	Bank 0	P-0	Bank 1	P-1	Bank 2	Bank 3
512KB	(4) 44256	(2) 41256	NONE	NONE	NONE	NONE
640KB	(4) 44256	(2) 41256	(4) 4464	(2) 41256	NONE	NONE
1MB	(4) 44256	(2) 41256	(4) 44256	(2) 41256	NONE	NONE
2MB	NONE	NONE	NONE	NONE	(2) 1M x 9	NONE
4MB	NONE	NONE	NONE	NONE	(2) 1M x 9	(2) 1M x 9