


BIOSTAR MICROTECH INTERNATIONAL CORPORATION

MB-1333/40RCS-A

Processor 80386SX/CX486SLC
Processor Speed 33/40MHz
Chip Set Unidentified
Max. Onboard DRAM 16MB
Cache None
BIOS AMI
Dimensions 220mm x 220mm
I/O Options None
NPU Options 80387SX



CONNECTIONS			
Purpose	Location	Purpose	Location
External battery	JP1	Turbo LED	JP5
Power LED & keylock	JP3	Turbo switch	JP6
Speaker	JP4	Reset switch	JP7

Continued on next page. . .

BIOSTAR MICROTECH INTERNATIONAL CORPORATION

MB-1333/40RCS-A

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper	Position
í CMOS memory normal operation	JP1	pins 2 & 3 closed
CMOS memory clear	JP1	pins 3 & 4 closed
External battery installed	JP1	pins 1, 2, 3 & 4 closed
í Monitor type select monochrome	JP2	Open
Monitor type select color	JP2	Closed

DRAM CONFIGURATION		
Size	Bank 0	Bank 1
512KB	(2) 256K x 9	NONE
1MB	(2) 256K x 9	(2) 256K x 9
2MB	(2) 1M x 9	NONE
4MB	(2) 1M x 9	(2) 1M x 9
8MB	(2) 4M x 9	NONE
16MB	(2) 4M x 9	(2) 4M x 9

CPU SPEED CONFIGURATION			
Speed	JP8	JP9	JP10
33MHz	pins 2 & 3 closed	pins 2 & 3 closed	pins 1 & 2 closed
40MHz	pins 1 & 2 closed	pins 2 & 3 closed	pins 2 & 3 closed