


ATRONICS INTERNATIONAL, INC.

ATI-1000

Processor	80286 (exact location unidentified)
Processor Speed	8MHz
Chip Set	Unidentified
Max. Onboard DRAM	1MB
Cache	None
BIOS	Unidentified
Dimensions	325mm x 300mm
I/O Options	None
NPU Options	80287 (exact location unidentified)



CONNECTIONS			
Purpose	Location	Purpose	Location
Speaker	J1	External battery	J4
Note: The location of J1 is unidentified.			

Continued on next page. . .

ATRONICS INTERNATIONAL, INC.

ATI-1000

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper/Switch	Position
í Factory configured - do not alter	JP3	Pins 2 & 3 closed
EPROM selected	JP4	Pins 2 & 3 closed
PROM selected	JP4	Pins 1 & 2 closed
Monitor type select color	SW1	Off
Monitor type select monochrome	SW1	On

DRAM CONFIGURATION
Note: This board accepts 640KB or 1MB of memory. The configurations are unidentified.

DRAM JUMPER CONFIGURATION	
Size	JP2
640KB	Pins 1 & 2, 5 & 6 closed
1MB	Pins 2 & 3, 5 & 6 closed

BIOS CONFIGURATION	
BIOS chips installed	JP1
2	Pins 2 & 3, 5 & 6 closed
4	Pins 1 & 2, 4 & 5 closed