

# COMPAQ COMPUTER CORPORATION

## PROLIANT 5000

<b>Processor</b>	Pentium Pro
<b>Processor Speed</b>	166/200MHz
<b>Chip Set</b>	Unidentified
<b>Video Chip Set</b>	Unidentified
<b>Maximum Onboard Memory</b>	4GB
<b>Maximum Video Memory</b>	Unidentified
<b>Cache</b>	256/512KB (located on Pentium Pro CPU)
<b>BIOS</b>	Unidentified
<b>Dimensions</b>	Unidentified
<b>I/O Options</b>	Fast SCSI-2 interface, parallel port, PS/2 mouse port, serial ports (2), RJ-45 connector, BNC connector (optional), VGA port
<b>NPU Options</b>	None

34407

CONNECTIONS	
Note: The location of the connectors is unidentified.	

USER CONFIGURABLE SETTINGS		
Function	Label	Position
í On board video enabled	S1/1	Off
On board video disabled	S1/1	On
í Chassis configuration lock enabled	S1/2	Off
Chassis configuration lock disabled	S1/2	On
í System installed in a tower chassis	S1/3	Off
System installed in a rack chassis	S1/3	On
í System boot from floppy controlled through configuration settings	S1/4	Off
System boot from floppy drive regardless of configuration settings	S1/4	On
í Password enabled	S1/5	Off
Password disabled	S1/5	On
í CMOS memory normal operation	S1/6	Off
CMOS memory clear	S1/6	On

DIMM CONFIGURATION	
Note: The configuration of the 4GB memory is unidentified.	

CACHE CONFIGURATION	
Note: 256KB/512KB cache is located on the Pentium Pro CPU.	

VIDEO MEMORY CONFIGURATION	
Note: The size of the video memory is unidentified.	

DRIVE SELECTION			
SCSI ID	ID0	ID1	ID2
5	On	Off	On
6	Off	On	On

MISCELLANEOUS TECHNICAL NOTE	
Note: Diagram not available.	