

COMPAQ COMPUTER CORPORATION

PROSIGNIA 200

Processor	Pentium
Processor Speed	166MHz
Chip Set	Unidentified
Video Chip Set	Unidentified
Maximum Onboard Memory	128MB (EDO supported)/256MB
Maximum Video Memory	Unidentified
Cache	512KB
BIOS	Unidentified
Dimensions	Unidentified
I/O Options	IDE interface, Ultra-Wide SCSI interface (optional), Fast-Wide SCSI interface (optional), parallel port, PS/2 mouse port, serial port, VGA port
NPU Options	None

34410

CONNECTIONS	
Purpose	Location
External battery	E9/pins 9 - 12
Note: The location of the connectors is unidentified.	

USER CONFIGURABLE SETTINGS		
Function	Label	Position
í Password enabled	E6	Pins 5 & 6 closed
Password disabled	E6	Pins 6 & 7 closed
í Factory configured - do not alter	SW1/3	Unidentified
í System boot from floppy controlled through configuration settings	SW2/1	Off
System boot from floppy drive regardless of configuration settings	SW2/1	On
í Factory configured - do not alter	SW2/2	Off
í Factory configured - do not alter	SW2/3	Off
í CMOS memory normal operation	SW2/4	Off
CMOS memory clear	SW2/4	On

DRAM CONFIGURATION
Note: If EDO memory is installed, the maximum amount of on board memory is 128MB. The configuration for the 128MB & 256MB are unidentified.

CACHE CONFIGURATION
Note: The location of 512KB cache is unidentified.

CPU SPEED SELECTION					
CPU speed	Clock speed	Multiplier	SW1/1	SW1/2	SW1/4
166MHz	66MHz	2.5x	On	Off	On

MISCELLANEOUS TECHNICAL NOTE
Note: Diagram not available.