


# HomeIT Platform



## Product Innovations Enable you to Lead a Technological Life

Our advanced facilities, powerful manpower and strict quality control system have reassured our competency and product quality to captivate both the local and international markets. To share our secret of success, contact us for a perfect solution.

\* TV RF Platform  
(NTSC/PAL)



\* Home Computer Platform



\* Wireless Input Devices



\* Internet Platform



**STB-6640S (HomeIT platform)**

\* Digital/ Analog  
Video Platform



**dar**ter

**Chang Tseng Technology Co., Ltd.**

5F., No. 335, Ban Nan Rd., Chung Ho, Taipei Hsien 235, Taiwan

Tel: 886-2-2246-2199 Fax: 886-2-2246-7205 E-mail: sales@darter.com.tw

Homepage: <http://www.darter.com.tw>

<http://www.globalsources.com/darter.co>




\* CRT/ TV Display Platform




\* Movies (DVD/ VCD)

# HomeIT Platform


STB-6610S




# HomeIT Platform



# HomeIT Platform STB-6610S



# SYSTEM BLOCK DIAGRAM



## Specifications

### HomeIT Platform Functions

- **CPU:**  
Pentium III®Coppermine™Celeron™ supported (With system bus frequencies of 66/100/133MHz).
- **Chipset:**  
VIA Apollo Pro133
- **Memory:**  
Onboard one 168-pin DIMM socket supports up to 512 Mbytes SDRAM.
- **Enhanced IDE:**  
Support up to four IDE devices. Supports Ultra DMA 33/66/100 mode with data transfer rate.
- **FDD interface:**  
Supports up to two floppy disk drives, 5.25" (360KB and 1.2MB) and /or 3.5" (720KB, 1.44MB, and 2.88MB).
- **Parallel port:**  
One parallel connector. Supports SPP, ECP and EPP modes.
- **Serial ports:**  
Two RS-232 serial connector. Ports can be configured as COM1, COM2 or disabled individually.
- **IR interface:**  
Supports one IrDA Tx/Rx header.
- **Keyboard/mouse connector:**  
Supports PS2 keyboard and PS/2 mouse. Supports Wireless PS2 keyboard and PS/2 mouse Pin Header
- **USB ports:**  
Supports dual USB port connector. 5 x 2 header supports dual USB ports.
- **AUDIO Interface:**  
Integrated high-fidelity AC' 97 CODEC. 18-bit stereo full duplex Óäcode,3D stereo expansion for simulated surround. Supports PC games and applications for SoundBlaster and SoundBlasterPro.

Supports Microsoft Windows SoundSystem Internal MIC-in, Line-in and Speaker-out interface reserved.

Full-duplex Operation for simultaneous record and playback.

- **GAME/MIDI port:**  
Support one game/midi connector.
- **PCI slot:**  
Two 32-bit PCI slot onboard.

### SSD Interface :

One 32-pin DIP socket supports M-systems DiskOnChip 2000 Series up to 288MB.

### LAN Interface :

LAN Interface

Supports one 100Base-T RJ-45 connector.

### Graphics/Video Interface :

TVia CyberPro 50xx Streaming Media Processors

Large write buffer allows sustained zero-wait-state bursts.

Support CRT connector.

Supports AV/S port for output TV.

Supports AV/S port for input video.

TV Encoder NTSC/PAL. NTSC

(640x480/720x480/800x600(option) @60Hz), PAL (800x600/720x540/640x480 @50Hz).

Alpha Blending, Hardware alpha blending of multiple video and graphics.

Two Simultaneous video ports, video capture, scaling, and VideoDirect™


VBI data pass through for Interacts.


Video Windows and Video Display,

Three video windows plus PIP.

## Software Support and Driver Utility-CD disk

- Microsoft Windows and AP demo:
- Linux and AP demo:
- Driver and Utility:
- Data sheet and Program guide:





STB-6610S (HomeIT platform)





# BOX FUNCTION


## HomeIT Platform AP Function

---




### Language Setup Select:

1. Enter number




2. Enter number



3. Three Point Select

( ) Regular Chinese   ( ) Sample Chinese   ( O ) English

Enter



4. Push the **OK** button

# HomeIT Platform AP Function

---



## Web Review (Phoenix Web)



Enter the right key "Alt" to exit

## HomeIT Platform AP Function

---



### E-mail



Enter "Ctrl" + "Q" to exit

# HomeIT Platform AP Function

---



# HomeIT Platform AP Function

---




## Remote Training



Enter "Ctrl" + "Q" to exit


# HomeIT Platform AP Function



---






## Multimedia (Video Only On TV Display)

You can find [Alpha Blending](#) Function on TV screen

Enter  to into TV Channels

Enter   to select TV Frequency Channel

Or Enter the TV Frequency Channel number

Enter Number    to exit


## HomeIT Platform AP Function

---




### Home Theater (Video Only On TV Display)

Enter



to into DVD Player

Function as below: Keyboard Number





# HomeIT Platform AP Function

---



## Fashion



Enter "Ctrl" + "Q" to exit


## HomeIT Platform AP Function

---



**Stock Market (Video Only On TV Display)**



Enter



to into “ Hang Seng Index A “

**You will find the PIP and Alpha Blending Function**

## Hang Seng Index A


Enter  ,  select item

Select item "3." Enter

Select item "1" Enter

Select item "2" Enter

Select item "2" Enter

Enter  to back

Select Item "9" Enter to exit

# HomeIT Platform AP Function

---



## Enjoy Life



Enter "Ctrl" + "Q" to exit