



## AFOX IG31-MA6

*Model Name: IG31-MA6*

*Chipset: Intel® G31 Express Chipset + ICH7*

*Socket: INTEL® Socket 775*

*Supports Intel Core™ 2 Duo / Core™ Duo / Pentium® D / Pentium® 4 / Celeron® D Processors*

*Dual channel DDR2, two memory slots*

*800 / 1066 / 1333MHz Memory up to 4GB*

*High speed USB interface*

*High quality audio special capacitor+independent audio block LED isolation line*

*Competent for multiple office needs*

*Low power consumption but high efficiency*

[DESCRIPTION](#)[SPECIFICATION](#)[BIOS / DRIVERS UPDATE](#)[REQUIREMENT](#)

<b>Platform</b>	Intel® Socket 775
<b>Model Name</b>	IG31-MA6
<b>Chipset</b>	Intel® G31 Express Chipset + ICH7
<b>CPU Supports</b>	Intel® Core™ 2 Quad / Duo / Extreme / Pentium® D / Pentium® 4 / Celeron® 4 Processors
<b>FSB</b>	800 / 1066 / 1333MHz
<b>Memory</b>	Dual Channel DDR2 800 / 1066 / 1333MHz
<b>Dimm</b>	2 x Memory Slots (Max. capacity of system memory 4GB)
<b>Onboard Graphics</b>	Integrated Intel® GMA 3100 graphics
<b>PCI/PCI-E Slots</b>	1 x PCI Express x16 slot
<b>SATA</b>	4 x SATA2
<b>IDE</b>	1 x IDE
<b>Audio</b>	Realtek 662 on board, Supports 6-channel audio-out
<b>LAN</b>	Realtek RTL8105 10/100Mbps Ethernet on board
<b>Back Panel I/Os</b>	1 x D-Sub (VGA) 6 x USB 2.0 Ports 1 x RJ-45 LAN Port 3 x HD Audio Jacks (Line in / Front Speaker / Microphone)
<b>ON-Board Pinheaders/Connectors</b>	1 x USB 2.0 pinheader (supports additional 2 USB 2.0s) 1 x Front Panel Audio pinheader
<b>BIOS</b>	Supports BIOS update
<b>Form Factor</b>	Micro-ATX (17 x 19 cm)
<b>Mounting</b>	4 mounting holes
<b>Accessories</b>	1 x SATA II cable 1 x I/O Rear Panel 1 x User Manual 1 x Driver CD

## PRODUCT

[Graphics Card](#)

[Motherboard](#)

[Mining Rig System](#)

[Memory](#)

[SSD](#)

[CPU Cooler](#)

[Power Supply](#)

[Mini PC](#)

## NEWS

[Hot News](#)

[Product Review](#)

[Event & Promotion](#)

## SERVICE & SUPPORT

[Warranty Policy](#)

[Download Center](#)

## ABOUT AFOX

[About AFOX](#)

[公司简介](#)

[Certificate](#)