

○ LS-P54CE

1. PCB Ver F1 CPU

| C P U | | | J11 |
|-----------------------------|--------|-----|---------------|
| Intel / AMD 75MHz | 50 MHz | 1.5 | 5-6, 7-8 |
| Cyrix P120+ | 50 MHz | 2 | 3-4, 5-6, 7-8 |
| Cyrix P133+ | 55 MHz | 2 | 3-4 |
| Intel / AMD 90/120MHz | 60 MHz | 1.5 | 7-8 |
| Intel / AMD 100/133MHz | 66 MHz | 1.5 | 5-6 |
| Intel 120MHz Cyrix P150+ | 60 MHz | 2 | 3-4, 7-8 |
| Intel 133MHz Cyrix P160+ | 66 MHz | 2 | 3-4, 5-6 |
| Intel 150MHz | 60 MHz | 2.5 | 1-2, 3-4, 7-8 |
| Intel 166MHz | 66 MHz | 2.5 | 1-2, 3-4, 5-6 |
| Intel 180MHz | 60 MHz | 3 | 1-2, 7-8 |
| Intel 200MHz | 66 MHz | 3 | 1-2, 5-6 |

2. PCB Ver F4 CPU

| C P U | | | J11 | J12 | J13 | J14 | JP11 |
|-----------------------------|-------|-----|---------|-----|-----|-----|------|
| Intel / AMD 75MHz | 50MHz | 1.5 | OFF | 1-2 | 1-2 | 1-2 | 1-2 |
| Cyrix P120+ | 50MHz | 2 | 3-4 | 1-2 | 1-2 | 1-2 | 1-2 |
| Cyrix P133+ | 55MHz | 2 | 3-4 | 2-3 | 1-2 | 1-2 | 1-2 |
| Intel / AMD 90/120MHz | 60MHz | 1.5 | OFF | 1-2 | 1-2 | 2-3 | 1-2 |
| Intel / AMD 100/133MHz | 66MHz | 1.5 | OFF | 1-2 | 2-3 | 1-2 | 1-2 |
| Intel 120MHz Cyrix P150+ | 60MHz | 2 | 3-4 | 1-2 | 1-2 | 2-3 | 1-2 |
| Intel 133MHz Cyrix P166+ | 66MHz | 2 | 3-4 | 1-2 | 2-3 | 1-2 | 1-2 |
| Intel 150MHz | 60MHz | 2.5 | 1-2,3-4 | 1-2 | 1-2 | 2-3 | 1-2 |
| Intel 166MHz | 66MHz | 2.5 | 1-2,3-4 | 1-2 | 2-3 | 1-2 | 1-2 |
| Intel 180MHz | 60MHz | 3 | 1-2 | 1-2 | 1-2 | 2-3 | 1-2 |
| Intel 200MHz | 66MHz | 3 | 1-2 | 1-2 | 2-3 | 1-2 | 1-2 |
| Intel MMX 166MHz | 66MHz | 2.5 | 1-2,3-4 | 1-2 | 2-3 | 1-2 | 3-4 |
| Intel MMX 200MHz | 66MHz | 3 | 3 | 1-2 | 2-3 | 1-2 | 3-4 |

3.

(LSI_LED1.BMP)

4.

JP15 - CMOS (ON)