

M2N-SLI Deluxe/Wireless Edition



Product Support For

M2N-SLI Deluxe/Wireless Edition

[Find Another Model >](#)

By registering your device, you can easily manage your product warranty, get technical support and keep track of your repair status.

[Register Product](#)

CPU / Memory
Support

Driver & Utility

FAQ

Manual &
Document

Warranty

CPU SUPPORT
















CPU Support

Memory / Device Support
















The following table shows the supported CPUs for this motherboard [Click here to search other motherboards.](#)

CPU	Validated since PCB	Validated since BIOS	Note
Athlon 64 3000+ (CN),512K,rev.F2,62W,SocketAM2	ALL	0201 GO	
Athlon 64 3200+ (CN),512K,rev.F2,62W,SocketAM2	ALL	0201 GO	
Athlon 64 3200+ (DE),512K,rev.G,45W,SocketAM2	ALL	0801 GO	
Athlon 64 3500+ (CN),512K,rev.F2,62W,SocketAM2	ALL	0201 GO	
















M2N-SLI Deluxe/Wireless Edition

Athlon 64 3500+ (CW),512K,rev.F2,62W,SocketAM2	ALL		
Athlon 64 3500+ (DE),512K,rev.G,45W,SocketAM2	ALL	0801 	
Athlon 64 3500+ (DH),512K,rev.F3,62W,SocketAM2	ALL	0801 	
Athlon 64 3800+ (CN),512K,rev.F2,62W,SocketAM2	ALL	0201 	
Athlon 64 3800+ (CW),512K,rev.F2,62W,SocketAM2	ALL	0307 	
Athlon 64 3800+ (DE),512K,rev.G,45W,SocketAM2	ALL	0801 	
Athlon 64 3800+ (DH),512K,rev.F3,62W,SocketAM2	ALL	0903 	
Athlon 64 4000+ (CW),512K,rev.F2,59W,SocketAM2	ALL	0609 	
Athlon 64 4000+ (DH),512K,rev.F3,62W,SocketAM2	ALL	0801 	
Athlon 64 FX-62 (CS),1MBx2,rev.F2,125W,SocketAM2	ALL	0201 	
Athlon 64 LE-1600+ (DH),1M,rev.F3,45W,SocketAM2	ALL	1203 	
Athlon 64 LE-1620+ (DH),1M,rev.F3,45W,SocketAM2	ALL	1203 	
Athlon 64 LE-1640+ (DH),1M,rev.F3,45W,SocketAM2	ALL	1203 	
Athlon 64 LE-1640+ (DP),512K,rev.G2,45W,SocketAM2	ALL	1302 	
Athlon 64 LE-1660+ (DP),512K,rev.G2,45W,SocketAM2	ALL	1404 	beta
















M2N-SLI Deluxe/Wireless Edition

Athlon 64 X2 3600+ (CU),512K,65W,rev.F2,SocketAM2	ALL	
Athlon 64 X2 3600+ (DD),1MB,65W,rev.G,SocketAM2	ALL	0609 
Athlon 64 X2 3800+ (CS),512Kx2,65W,rev.F2,SocketAM2	ALL	0603 
Athlon 64 X2 3800+ (CU),512Kx2,35W,rev.F2,SocketAM2	ALL	0307 
Athlon 64 X2 3800+ (CU),512Kx2,65W,rev.F2,SocketAM2	ALL	0203 
Athlon 64 X2 3800+ (CU),512Kx2,rev.F2,89W,SocketAM2	ALL	0201 
Athlon 64 X2 3800+ (CZ),512Kx2,65W,rev.F3,SocketAM2	ALL	0502 
Athlon 64 X2 4000+ (CS),1MBx2,rev.F2,65W,SocketAM2	ALL	0307 
Athlon 64 X2 4000+ (CS),1MBx2,rev.F2,89W,SocketAM2	ALL	0201 
Athlon 64 X2 4000+ (DD),1MB,rev.G,65W,SocketAM2	ALL	0609 
Athlon 64 X2 4200+ (CU),512Kx2,rev.F2,65W,SocketAM2	ALL	0307 
Athlon 64 X2 4200+ (CU),512Kx2,rev.F2,89W,SocketAM2	ALL	0201 
Athlon 64 X2 4200+ (DD),512Kx2,rev.G1,65W,SocketAM2	ALL	1201 
Athlon 64 X2 4200+ (DO),512Kx2,rev.G2,65W,SocketAM2	ALL	1203 
Athlon 64 X2 4400+ (CS),1MBx2,65W,rev.F2,SocketAM2	ALL	0307 












M2N-SLI Deluxe/Wireless Edition

Athlon 64 X2 4400+ (CS),1MBx2,rev.F2,89W,SocketAM2	ALL		
Athlon 64 X2 4400+ (DD),1MB,rev.G,65W,SocketAM2	ALL	0609 	
Athlon 64 X2 4400+ (DO),1MB,rev.G2,65W,SocketAM2	ALL	1201 	
Athlon 64 X2 4600+ (CU),512Kx2,rev.F2,65W,SocketAM2	ALL	0307 	
Athlon 64 X2 4600+ (CU),512Kx2,rev.F2,89W,SocketAM2	ALL	0201 	
Athlon 64 X2 4600+ (CZ),1MB,rev.F3,65W,SocketAM2	ALL	0903 	
Athlon 64 X2 4600+ (DO),1M,rev.G2,65W,SocketAM2	ALL	1404 	beta
Athlon 64 X2 4800+ (CS),1MBx2,rev.F2,65W,SocketAM2	ALL	0307 	
Athlon 64 X2 4800+ (CS),1MBx2,rev.F2,89W,SocketAM2	ALL	0201 	
Athlon 64 X2 4800+ (DD),1MB,rev.G,65W,SocketAM2	ALL	0609 	
Athlon 64 X2 4800+ (DO),1MB,rev.G2,65W,SocketAM2	ALL	1201 	
Athlon 64 X2 5000+ (CS),1MB,rev.F2,89W,SocketAM2	ALL	0503 	
Athlon 64 X2 5000+ (CU),512Kx2,rev.F2,89W,SocketAM2	ALL	0201 	
Athlon 64 X2 5000+ (CZ),1MB,rev.F3,65W,SocketAM2	ALL	1102 	
Athlon 64 X2 5000+ (CZ),1MB,rev.F3,89W,SocketAM2	ALL	0609 	














M2N-SLI Deluxe/Wireless Edition

Athlon 64 X2 5000+ (DD),1MB,rev.G,65W,SocketAM2	ALL		
Athlon 64 X2 5000+ (DO),1MB,rev.G2,65W,SocketAM2	ALL	1201	
Athlon 64 X2 5000+ (DS),1MB,rev.G2,65W,SocketAM2	ALL	1203	
Athlon 64 X2 5200+ (CS),1MBx2,rev.F2,89W,SocketAM2	ALL	0503	
Athlon 64 X2 5200+ (CZ),2MB,rev.F3,65W,SocketAM2	ALL	0903	
Athlon 64 X2 5200+ (CZ),2MB,rev.F3,89W,SocketAM2	ALL	0609	
Athlon 64 X2 5200+ (DD),1MB,rev.G,65W,SocketAM2	ALL	0407	
Athlon 64 X2 5200+ (DO),1MB,rev.G2,65W,SocketAM2	ALL	1201	
Athlon 64 X2 5400+ (CZ),1M,rev.F3,89W,SocketAM2	ALL	0609	
Athlon 64 X2 5400+ (DO),1M,rev.G2,65W,SocketAM2	ALL	1403	
Athlon 64 X2 5400+ (DS),1M,rev.G2,65W,SocketAM2	ALL	1603	
Athlon 64 X2 5600+ (CZ),2MB,rev.F3,89W,SocketAM2	ALL	0609	
Athlon 64 X2 6000+ (CZ),2MB,rev.F3,125W,SocketAM2	ALL	0702	
Athlon 64 X2 6000+ (CZ),2MB,rev.F3,89W,SocketAM2	ALL	1102	
Athlon 64 X2 6000+ (DO),1MB,rev.G2,89W,SocketAM2	ALL	1502	

M2N-SLI Deluxe/Wireless Edition

Athlon 64 X2 6400+ (CZ),2MB,rev.F3,125W,SocketAM2	ALL		
Athlon 64 X2 6500+ ,2.3GHz,1MB,rev.B3,AD6500WCJ2BGH,95W,SocketAM2	ALL	1604 	
Athlon IIX2 215(ADX215OCK22GQ),2.7GHz,512KB,rev.C2,65W,SocketAM3	ALL	5001 	beta, please note this version has removed LAN option ROM
Athlon IIX2 240e(AD240EHDK23GQ),2.8GHz,1MB,rev.C2,45W,SocketAM3	ALL	5001 	beta, please note this version has removed LAN option ROM
Athlon IIX2 255(ADX255OCK23GM),3.1GHz,512KB,rev.C3,65W,SocketAM3	ALL	5001 	beta, please note this version has removed LAN option ROM
Athlon IIX3 405e(AD405EHDK32GM),2.3GHz,512KB,rev.C3,45W,SocketAM3	ALL	5001 	beta, please note this version has removed LAN option ROM
Athlon IIX3 440(ADX440WFK32GI),3.0GHz,512KB,rev.C2,95W,SocketAM3	ALL	5001 	beta, please note this version has removed LAN option ROM
Athlon IIX3 445(ADX445WFK32GM),3.1GHz,512KB,rev.C3,95W,SocketAM3	ALL	5001 	beta, please note this version has removed LAN option ROM
Athlon IIX4 605e(AD605EHDK42GM),2.3GHz,512KB,rev.C3,45W,SocketAM3	ALL	5001 	beta, please note this version has removed LAN option ROM
Athlon IIX4 635(ADX635WFK42GI),2.9GHz,512KB,rev.C2,95W,SocketAM3	ALL	5001 	beta, please note this version has removed LAN option ROM
Athlon IIX4 640(ADX640WFK42GM),3.0GHz,512KB,rev.C3,95W,SocketAM3	ALL	5001 	beta, please note this version has removed LAN option ROM

M2N-SLI Deluxe/Wireless Edition

Athlon X2 4050e (DO),1M,rev.G2,45W,SocketAM2	ALL		beta
Athlon X2 4450e (DO),1M,rev.G2,45W,SocketAM2	ALL	1404 	
Athlon X2 4850e (DO),1M,rev.G2,45W,SocketAM2	ALL	1404 	beta
Athlon X2 5000+ (DU),1MB,rev.G2,65W,SocketAM2	ALL	1502 	
Athlon X2 5050e (DO),1MB,rev.G2,45W,ADH5050IAA5DO,SocketAM2	ALL	1604 	
Athlon X2 7450+ ,2.4GHz,2MB,rev.B3,AD7450WCJ2BGH,95W,SocketAM2+	ALL	1701 	
Athlon X2 7550+ ,2.5GHz,2MB,rev.B3,AD7550WCJ2BGH,95W,SocketAM2+	ALL	1701 	
Athlon X2 7750+ ,2.7GHz,2MB,rev.B3,AD7750WCJ2BGH,95W,SocketAM2+	ALL	1701 	
Athlon X2 7750+ ,2.7GHz,2MB,rev.B3,AD775ZWCJ2BGH,95W,SocketAM2+	ALL	1701 	
Athlon X2 7850+ ,2.8GHz,2MB,rev.B3,AD785ZWCJ2BGH,95W,SocketAM2+	ALL	1701 	
Athlon X2 BE-2300 (DD),1M,45W,rev.G1,SocketAM2	ALL	1003 	
Athlon X2 BE-2300 (DO),1M,45W,rev.G2,SocketAM2	ALL	1203 	
Athlon X2 BE-2350 (DD),1M,45W,rev.G1,SocketAM2	ALL	1003 	
Athlon X2 BE-2350 (DO),1M,45W,rev.G2,SocketAM2	ALL	1203 	
Athlon X2 BE-2400 (DO),1M,45W,rev.G2,SocketAM2	ALL	1203 	














M2N-SLI Deluxe/Wireless Edition

Opteron 1212, 2.00G, 2M/L2, rev.F3, 103W, SocketAM2	ALL			
Opteron 1212HE, 2.00G, 2M/L2, rev.F3, 65W, SocketAM2	ALL	0801		
Opteron 1214, 2.20GHz, 2M/L2, rev.F3, 103W, SocketAM2	ALL	0801		
Opteron 1216, 2.40G, 2M/L2, rev.F2, SocketAM2	ALL	0801		
Opteron 1216, 2.40G, 2M/L2, rev.F3, 103W, SocketAM2	ALL	0801		
Opteron 1218, 2.60G, 2M/L2, rev.F3, 103W, SocketAM2	ALL	0801		
Opteron 1220, 2.80G, 2M/L2, rev.F3, 103W, SocketAM2	ALL	0801		
Opteron 1220SE, 2.80G, 2M/L2, rev.F2, SocketAM2	ALL	0605		
Phenom IIX2 550 (HDZ550WFK2DGI),3.1GHz,80W,rev.C2,SocketAM3,Dual-Core	ALL	5001		beta, please note this version has removed LAN option ROM
Phenom IIX2 555(HDZ555WFK2DGM),3.2GHz,512KB,rev.C3,80W,SocketAM3	ALL	5001		beta, please note this version has removed LAN option ROM
Phenom IIX3 705e (HD705EOCK3DGI),2.5GHz,65W,rev.C2,SocketAM3,Triple-Core	ALL	5001		beta, please note this version has removed LAN option ROM
Phenom IIX3 715 (HDZ715WCJ3DGI),2.8GHz,95W,rev.C2,SocketAM2+,Triple-Core	ALL	5001		beta, please note this version has removed LAN option ROM
Phenom IIX3 740 (HDZ740WFK3DGI),3.0GHz,95W,rev.C2,SocketAM3,Triple-Core	ALL	5001		beta, please note this version has removed LAN option ROM
















M2N-SLI Deluxe/Wireless Edition

Phenom IIX4 820 (HDX820WFK4FGI),2.8GHz,95W,rev.C2,SocketAM3,Quad-Core	ALL	5001 	note this version has removed LAN option ROM
Phenom IIX4 905e (HD905EOCK4DGI),2.5GHz,65W,rev.C2,SocketAM3,Quad-Core	ALL	5001 	beta, please note this version has removed LAN option ROM
Phenom IIX4 910E(HD910EOCK4DGM),2.6GHz,65W,rev.C3,SocketAM3,Quad-Core	ALL	5001 	beta, please note this version has removed LAN option ROM
Phenom IIX4 925 (HDX925WFK4DGI),2.8GHz,95W,rev.C2,SocketAM3,Quad-Core	ALL	5001 	beta, please note this version has removed LAN option ROM
Phenom IIX4 945 (HDX945WFK4DGM),3.0GHz,2048KB,95W,rev.C3,SocketAM3,Quad-Core	ALL	5001 	beta, please note this version has removed LAN option ROM
Phenom X3 8250e (HD8250ODJ3BGH),1.9GHz,rev.B3,65W,SocketAM2+,Triple-Core	ALL	1603 	
Phenom X3 8400 (HD8400WCJ3BGD),2.1GHz,rev.B2,95W,SocketAM2+,Triple-Core	ALL	1404 	
Phenom X3 8450 (HD8450WCJ3BGH),2.1GHz,rev.B3,95W,SocketAM2+,Triple-Core	ALL	1502 	
Phenom X3 8450e (HD8450ODJ3BGH),2.1GHz,rev.B3,65W,SocketAM2+,Triple-Core	ALL	1603 	
Phenom X3 8550 (HD8550WCJ3BGH),2.2GHz,rev.B3,95W,SocketAM2+,Triple-Core	ALL	1603 	
Phenom X3 8600(HD8600WCJ3BGD),2.3GHz,95W,rev.B2,SocketAM2+,Triple-Core	ALL	1404 	
Phenom X3 8650 (HD8650WCJ3BGH),2.3GHz,95W,rev.B3,SocketAM2+,Triple-Core	ALL	1502 	
Phenom X3 8750 (HD8750WCJ3BGH),2.4GHz,rev.B3,95W,SocketAM2+,Triple-Core	ALL	1502 	

M2N-SLI Deluxe/Wireless Edition

Phenom X3 8750 (HD875ZWCJ3BGH),2.4GHz,rev.B3,95W,SocketAM2+,Triple-Core	ALL	
Phenom X3 8850 (HD8850WCJ3BGH),2.4GHz,rev.B3,95W,SocketAM2+,Triple-Core	ALL	1604 
Phenom X4 9100e (HD9100BJ4BGD),1.8GHz,65W,rev.B2,SocketAM2+,Quad-Core	ALL	1404 
Phenom X4 9150 (HD9150ODJ4BGH),1.8GHz,65W,rev.B3,SocketAM2+,Quad-Core	ALL	1502 
Phenom X4 9350 (HD9350ODJ4BGH),2.0GHz,65W,rev.B3,SocketAM2+,Quad-Core	ALL	1502 
Phenom X4 9450 (HD9450ODJ4BGH),2.1GHz,65W,rev.B3,SocketAM2+,Quad-Core	ALL	1604 
Phenom X4 9500 (HD9500WCJ4BGD),2.2GHz,rev.B2,95W,SocketAM2+,Quad-Core	ALL	1302 
Phenom X4 9550 (HD9550WCJ4BGH),2.2GHz,rev.B3,95W,SocketAM2+,Quad-Core	ALL	1502 
Phenom X4 9600 (HD9600WCJ4BGD),2.3GHz,95W,rev.B2,SocketAM2+,Quad-Core	ALL	1302 
Phenom X4 9600 (HD960ZWCJ4BGD),2.3GHz,95W,rev.B2,SocketAM2+,Quad-Core	ALL	1403 
Phenom X4 9650 (HD9650WCJ4BGH),2.3GHz,95W,rev.B3,SocketAM2+,Quad-Core	ALL	1502 
Phenom X4 9750 (HD9750WCJ4BGH),2.4GHz,95W,rev.B3,SocketAM2+,Quad-Core	ALL	1502 
Phenom X4 9750 (HD9750XAJ4BGH),2.4GHz,125W,rev.B3,SocketAM2+,Quad-Core	ALL	1502 
Phenom X4 9850 (HD9850WCJ4BGH,rev.B3,SocketAM2+,Quad-Core	ALL	1604 
Phenom X4 9850 (HD9850XAJ4BGH),2.5GHz,125W,rev.B3,SocketAM2+,Quad-Core	ALL	1502 

M2N-SLI Deluxe/Wireless Edition

(HD985ZXAJ4BGH),2.5GHz,125W,rev.B3,SocketAM2+,Quad-Core	ALL			
Phenom X4 9950 (HD995ZXAJ4BGH),2.6GHz,125W,rev.B3,SocketAM2+,Quad-Core	ALL	1604		
Sempron 140,SDX140HBK13GQ,2.7GHz,1024K,rev.C2,45W,SocketAM3	ALL	5001		beta, please note this version has removed LAN option ROM
Sempron 2100+ (DD),512K,rev.G1,65W,SocketAM2	ALL	1404		
Sempron 2100+ (DO),512K,rev.G2,65W,SocketAM2	ALL	1404		
Sempron 2800+ (CN),128K,rev.F2,62W,SocketAM2	ALL	0201		
Sempron 3000+ (CN),256K,rev.F2,62W,SocketAM2	ALL	0201		
Sempron 3200+ (CN),128K,rev.F2,62W,SocketAM2	ALL	0201		
Sempron 3200+ (CW),256K,rev.F2,62W,SocketAM2	ALL	0201		
Sempron 3400+ (CN),256K,rev.F2,62W,SocketAM2	ALL	0201		
Sempron 3400+ (CW),256K,rev.F2,62W,SocketAM2	ALL	0201		
Sempron 3500+ (CN),128K,rev.F2,62W,SocketAM2	ALL	0201		
Sempron 3600+ (CN),256K,rev.F2,62W,SocketAM2	ALL	0201		
Sempron 3600+ (CW),256K,rev.F2,62W,SocketAM2	ALL	1003		
Sempron 3800+ (CN),256K,rev.F2,62W,SocketAM2	ALL	0201		

M2N-SLI Deluxe/Wireless Edition

Sempron LE-1100 (DE),256K,rev.G1,45W,SocketAM2	ALL	GO
Sempron LE-1150 (DE),256K,rev.G1,45W,SocketAM2	ALL	1102 GO
Sempron LE-1200 (DE),512K,rev.G2,45W,SocketAM2	ALL	1203 GO
Sempron LE-1200 (DP),512K,rev.G2,45W,SocketAM2	ALL	1604 GO
Sempron LE-1250 (DP),512K,rev.G2,45W,SocketAM2	ALL	1203 GO
Sempron LE-1300 (DP),512K,rev.G2,45W,SocketAM2	ALL	1203 GO

NEED HELP?

[✉ Email Us](#) [📍 Find service locations](#)

Shop and Learn			Learn More	Support	About Us
Mobile	Workstations	Wired Networking	Asus Design Center	Check Repair Status	About ASUS
Phones	Accessories	Intelligent Robots		ASUSPRO	Find Service Locations
Accessories	Motherboards / Components	AIoT & Industrial Solutions	Automotive Solutions		Product Registration
Laptops	Motherboards	Servers	AVC Licensing Notice	Email Us	About CSR for global
For Home	Graphics Cards	Smart Home	ASUS Blog	Call Us	Press Room
For Work	Gaming Cases	Accessories		Security Advisory	ASUSTOR Inc.
For Creators	Cooling	Keyboards	ASUS Support Videos	MyASUS	UniMax Electronics Inc.
For Students	Power Supply Units	Mice and Mouse Pads			
For Gaming	Sound Cards	Headsets and Audio			
Accessories	Optical Drives	Streaming Kits			
Displays / Desktops	Data Storage	Apparel Bags and Gear			
Monitors	External Graphics Docks	Cases and Protection			
Projectors	Networking / IoT / Servers	Adapters and Chargers			

M2N-SLI Deluxe/Wireless Edition

Mini PCs

Whole Home Mesh WiFi System

Gimbal

Business Network Solutions

