

### Section 3 - 1 Connectors

Switch	:J24
Switch	:J21
LED	:J22
Reset & Power LED	:J25
	:J26
Keyboard LED	:J10
Hard Disk Connector	:PRI_IDE
Secondary Hard Disk Connector	:SEC_IDE
COM1 Connector	:COM1
COM2 Connector	:COM2
Floppy Drive Connector	:FDD
Parallel Port Connector	:PRN
Mouse Connector	:J3

### Section 3 - 2 Jumper Settings

#### Cache Setting

	J12, J13, J14	J15	J16	J17
	2 - 3	In	Out	Out
	2 - 3	Out	In	Out
	2 - 3	Out	Out	In
	1 - 2	Out	Out	Out

#### CPU Type Setting

	CPU	JJ1	JC1	JH1	JD1	JE1	JF1	JB1	JA1	JG1
Intel	SX	1-2	x	x	x	x	x	2-3	2-3	x
	DX/DX2	1-2	x	x	x	1-2	x	1-2 3-4	2-3	x
	DX4/P24C	1-2	x	x	x	1-2	2-3	1-2 3-4	1-2 3-4	2-3
	P24D	2-3	1-2	2-3	1-2	1-2	2-3	1-2 3-4	1-2 3-4	x
	P24T	2-3	x	x	x	2-3	x	1-2 3-4	1-2	x
	Pentium Overdrive	2-3	x	x	x	2-3	2-3	1-2 3-4	1-2	x
	486 Overdrive	1-2	x	x	x	2-3	x	1-2 3-4	2-3	x
	P23S	1-2	x	x	x	x	2-3	2-3	1-2 3-4	x
	P4S, P24S	1-2	x	x	x	1-2	2-3	1-2 3-4	1-2 3-4	x
AMD	DX	1-2	x	x	x	1-2	x	1-2 3-4	2-3	x
	DX2	1-2	x	x	x	1-2	x	1-2 3-4	2-3	2-3
	DX4 (WT)	1-2	x	x	x	1-2	x	1-2 3-4	2-3	x
	DX4+ (WB)	2-3	1-2	2-3	1-2	1-2	2-3	1-2 3-4	1-2 3-4	x
	DX5 (5x86)	2-3	1-2	2-3	1-2	1-2	2-3	1-2 3-4	1-2 3-4	1-2
Cyrix	S/S2	1-2	2-3	1-2	2-3	1-2	3-4	2-3	1-2	4-5
	DX/DX2/DX2-V	1-2	2-3	1-2	2-3	1-2	2-3	1-2 3-4	1-2	x
	M8/5x86/M9/M1sc x2	2-3	1-2	2-3	x	1-2	2-3	1-2 3-4	1-2 3-4	1-2
	M8/5x86/M9/M1sc x3	2-3	1-2	2-3	x	1-2	2-3	1-2 3-4	1-2 3-4	x
Intel	DX2/DX4	1-2	2-3	1-2	2-3	1-2	2-3	1-2 3-4	1-2	x
ST	DX2	1-2	2-3	1-2	2-3	1-2	2-3	1-2 3-4	1-2	x
	DX4	1-2	1-2	2-3	x	1-2	2-3	1-2 3-4	1-2 3-4	x

#### ECF Function

	J4	J5
DMA 3	2 - 3	2 - 3
DMA 1	1 - 2	1 - 2


#### Cache Setting

Cache Size	TAG	Data	J18
128KB	8Kx8	32Kx8	1 - 2
256KB	32Kx8	64Kx8	1 - 2
512KB	32Kx8	128Kx8	2 - 3


#### CPU Clock setting

Frequency	J8	J9	J11	J23
25/50/75 MHz	Out	Out	1 - 2	Out
33/66/100/133 MHz	In	In	1 - 2	Out
40/80/120/160 MHz	Out	In	2 - 3	In
50/100/150 MHz	In	Out	2 - 3	In


**:PU Type Setting**




AMD DX5 5x86




AMD DX2 (WT)



Cyrix 5x86 M8 M9 M1sc (x3)




Intel DX4 P24C



386 DX4




AMD DX4+ (WB)



AMD DX4 (WT)



Cyrix DX DX2 (WB) / TI DX2 DX4 ST DX2



Intel DX2 DX

**on 3 - 3 Jumper Location Diagram**

