



MANUAIS DE MOTHERBOARDS JBOND

PCI600N/610N/620N



- **Socket 370 (Intel PPGA)**
- **Intel 82443BX Chipset for PCI600N;**
VIA VT82C693 Chipset for PCI610N;
Intel 82443ZX Chipset for PCI620N.
- **SMC FDC37M602 Power Multi I/O Chip.**
- **Dimensions: 30.5cm x 17.7cm (12 inches x 7 inches) ATX form.**
- Award PnP PCI flash BIOS.
- Three 168-pin DIMM sockets for PCI600N/610N; Two 168-pin DIMM sockets for PCI620N.
- Two Enchance IDE sockets (up to four IDE devices) support fast ATA-2, ATAPI, and Ultra DMA/33 functions.
- One Floppy socket supports two floppy drivers with 360K, 720K, 1.22M, 1.44M, and 2.88M bytes.
- One AGP slot supports x1 and x2 AGP card.
- Four PCI slots. (PCI spec. V2.1)
- Two ISA slots. (1 PCI/ISA shared slot)
- PS/2 keyboard and PS/2 mouse connectors on board.
- Two Serial Port sockets.
- One Parallel Port socket supports SPP, EPP, and ECP.
- Two USB Port connectors on board.
- One FIR (Fast IrDA) Port connector on board (transfer rate up to 4MB/s).
- **(New) LAN wake-up function.**
- **(New) Modem wake-up function to switch system power on.**
- **(New) Automatic frequency reduction in case of CPU overheating.**
- **Creative(TM) SB link ready function.**
- **(Optional) On board CMI8330 real 3D HRTF Sound Chip.**
- **(Optional) System hardware health monitor.**

1. CPU Jumper Settings

* BIOS automatically detects CPU system speed.

Intel Celeron	JP2 PIN 1	JP2 PIN 2	JP2 PIN 3	JP2 PIN 4	JP1 PIN 1
233MHz	ON	NC	ON	NC	1-2
266MHz	ON	ON	NC	ON	1-2
300MHz	ON	NC	NC	ON	1-2
333MHz	ON	ON	NC	NC	1-2
366MHz	ON	NC	NC	NC	1-2
400MHz	NC	ON	ON	ON	1-2
433MHz	NC	NC	ON	ON	1-2
466MHz	NC	ON	ON	NC	1-2
500MHz	NC	NC	ON	NC	1-2
533MHz	NC	ON	NC	ON	1-2

Note:

- ON - jumper block short
- NC- jumper block open

2. Clear CMOS Data Jumper Settings

Operating Mode	CLS
Normal Operating (default)	Short 1-2
Clear CMOS Data	Short 2-3 while computer powered OFF

3. Support DIMM Module List

- Each DIMM socket supports 4M to128M bytes (for 16Mbit technology) or 8M to256M bytes (for 64Mbit technology) DIMM module.
- Vcc provides 3.3v
- Support SDRAM-II, SDRAM and EDO DIMM modules.

4. (Optional) On board Sound Chip Jumper Settings

Operating Mode	SJP1
Enable (default)	NC
Disable	ON

5. (Optional) MIC IN Select Jumper Settings

Operating Mode	SJP2
Normal Operating (default)	NC
Special MIC IN	ON

6. Support Year 2000 Compliance

- BIOS version 1.00 or later supports Year 2000 compliance.

7. Support LS-120 Zip Driver Boot Function

8. Support SCSI/CD-ROM Function

9. Support INT 13 Expansion Mode (control above 8.4 GB IDE Hard Disk)