

DTK Computers

Technical Information Sheet for PIM-1001

S=shorted, 0=open

DIP switch 1=on 0=off

J1:Speaker

J2:Power LED

<1> Negative Lead

<2> Positive Lead

J3:Turbo LED

<1> Positive Lead

<2> Negative Lead

J4:Hardware Turbo Switch

S Turbo

0 Normal

RAM Type

Memory Size	RAM Type Bank 0	Bank 1
512k	41000x4	none
640k	41100x4	44256x1

W1:Reset Connector

12

W2:Monitor Selection ::

1-2 3-4 Type 34

0 0 Monochrome

S 0 Color (80x25)

0 S Color (40x25)

ANY EGA or VGA

W3:ROM BIOS Size

1-2 S 27128 (16K)

2-3 S 2764 (8K)

W4:Keyboard Lock

S Enable

0 Locked

Power Connector

<1> N/C

<2> +5 VDC

<3> +12 VDC

<4> -12 VDC

<5> Ground

<6> Ground

<7> Ground

<8> Ground

<9> -5 VDC

<10> +5 VDC

<11> +5 VDC

<12> +5 VDC