



Packard Bell 88 M/Board

[Home](#)
[What's New](#)
[Contact Us](#)

Search the Site

Find

powered by
[FreeFind](#)

[Acer](#)
[Advent](#)
[Amstrad](#)
[Apple](#)
[Canon](#)
[Compaq](#)
[CTX](#)
[Epson](#)
[Hewlett Packard](#)
[Mitsubishi/Apricot](#)
[Packard Bell](#)
[Other Manufact.](#)

[File Extensions](#)
[Humour](#)
[Links](#)
[Microsoft](#)
[Reference](#)
[Scanner Support](#)

Specification

- **Battery** : Rechargeable, soldered on motherboard
- **BIOS** : 2 X 8KB - Phoenix BIOS chassis Phoenix 2.03 SF Phoenix 2.03 SE (latest)
- **Cache** : N/A
- **Clock/Driver** : (RTC)
- **CPU** : 8088-2 Keyboard Switches : (Ctrl)-(Alt)-(-) = 4.77 MHz, (Ctrl)-(Alt)-(+)= 8 MHz 8087-2 (optional)
- **Drive Cavities** : 2 X half-height (exposed)
- **Front Panel** : Power switch : FUR Keyboard Port : FLL
- **Interfaces** :
 - 1x DB-25 Parallel Port
 - 1x RS-232C, DB-9 Serial Port
 - 1x 5-pin Keyboard Port
- **I/O expansion slots** : 7 X 8-bit ISA
- **Keyboard** : 101-Key Enhanced AT
- **Power Supply** : 135 Watts 115V : 60Hz/230v : 50Hz
- **RAM** : Standard on motherboard : 512Kb or 640Kb. Can NOT be upgraded on motherboard
- **Speaker** : Internal - cone in front
- **Video** : Often shipped with CGA.

DIP Switches

CPU Board

Function	S1	S2	S3	S4	S5	S6	S7	S8
Test	OFF	--	--	--	--	--	--	--
Math Coprocessor Not Installed	--	ON	--	--	--	--	--	--
Math Coprocessor installed	--	OFF	--	--	--	--	--	--
No Function	--	--	OFF	OFF	--	--	--	--
Graphics - Low Res	--	--	--	--	OFF	ON	--	--

Graphics - High Res	--	--	--	--	ON	OFF	--	--
Graphics - Mono	--	--	--	--	OFF	OFF	--	--
Floppy Drive	--	--	--	--	--	--	ON	ON
Floppy Drive	--	--	--	--	--	--	ON	OFF

Video Card

Note - The DIP Switch is located on the metal bracket on the Video Card.

Function	S1	S2	S3	S4	S5	S6	S7	S8
Monitor Emulation - Mono	ON	--	--	--	--	--	--	--
Monitor Emulation - CGA	OFF	--	--	--	--	--	--	--
Monitor Type - TTL Mono	--	OFF	ON	OFF	OFF	ON	-	--
Monitor Type - CGA Colour	--	ON	OFF	ON	OFF	ON	--	--
Monitor Type - Composite Mono	--	ON	OFF	ON	OFF	ON	--	--
Monitor Type - Composite Colour	--	ON	OFF	ON	ON	ON	--	--
Reserved	--	--	--	--	--	--	ON	ON
