
BOCA RESEARCH, INC. I O A T 4 3

Card Type Chipset Controller I/O Options Maximum DRAM MULTI I/O National Semiconductor

Parallel port, Serial port (2)

N/A



CONNECTIONS				
Purpos :	Location	Purpos ;	Location	
Serial port 2	J1	Serial port 1	J2	
Parallel port	J3			

PARALLEL PORT BASE I/O ADDRESS SELECTION			
Address	J5/C		
LPT1	Pins 1 & 2 closed		
LPT2	Pins 2 & 3 closed		

SERIAL PORT 1 BASE I/O ADDRESS SELECTION			
Address	J5/A		
COM1	Pins 1 & 2 closed		
COM3	Pins 2 & 3 closed		

SERIAL PORT 2 BASE I/O ADDRESS SELECTION			
Address	J5/B		
COM2	Pins 1 & 2 closed		
COM4	Pins 2 & 3 closed		

Continued next page...

BOCA RESEARCH, INC. I O A T 4 3

. . . continued from previous page.

PARALLEL PORT INTERRUPT SELECTION			
IRQ	J5/D		
í 7	Pins 2 & 3 closed		
5	Pins 1 & 2 closed		

SERIAL PORT 1 INTERRUPT SELECTION				
IRQ	J5/E pins 1 & 2	J5/F pins 1 & 2	J5/G pins 1 & 2	J5/H pins 1 & 2
í 4	Open	Closed	Open	Open
3	Closed	Open	Open	Open
5	Open	Open	Closed	Open
9	Open	Open	Open	Closed

SERIAL PORT 2 INTERRUPT SELECTION					
IRQ	IRQ J5/E pins 2 & 3 J5/F pins 2 & 3 J5/G pins 2 & 3 J5/H pins 2 & 3				
í3	Closed	Open	Open	Open	
4	Open	Closed	Open	Open	
5	Open	Open	Closed	Open	
9	Open	Open	Open	Closed	