AMERICAN MEGATRENDS, INC.

386 AT MARK II SYSTEM MOTHERBOARD

Processor 80386


Processor Speed 16/20/25/33MHz Chip Set Unidentified **Video Chip Set** None

Maximum Onboard Memory 16MB (8MB on external memory card)

Maximum Video Memory None Cache None **BIOS** AMI

Dimensions 355mm x 304mm I/O Options External memory card

NPU Options 80387/3167



Continued on next page. . .

AMERICAN MEGATRENDS, INC. 386 AT MARK II SYSTEM MOTHERBOARD

. . . continued from previous page

CONNECTIONS			
Purpose	Location	Purpose	Location
Turbo LED	J1	Power LED & keylock	J8
Reset switch	J2	External battery	J9
Speaker	J7	External memory card	SL1

USER CONFIGURABLE SETTINGS			
Function	Label	Position	
í Factory configured - do not alter	J26	Unidentified	
Factory configured - do not alter	SW/1	Off	
Monitor type select color	SW/2	On	
Monitor type select monochrome	SW/2	Off	

	DRAM CONFIGURATION	
Size	Bank 0	Bank 1
1MB	(36) 41256	None
1MB	None	(4) 256K x 9
2MB	(36) 41256	(4) 256K x 9
4MB	(36) 411000	None
4MB	None	(4) 1M x 9
5MB	(36) 41256	(4) 1M x 9
5MB	(36) 411000	(4) 256K x 9
8MB	(36) 411000	(4) 1M x 9
16MB	None	(4) 4M x 9
Note: Board will accept 441000 chips but the configuration was not available.		

DRAM JUMPER CONFIGURATION			
Bank 0 chips	Bank 1 chips	J27	
Installed	Not installed	Pins 1 & 2, 3 & 4 closed	
Not installed	Installed	Pins 2 & 3, 4 & 5 closed	
41256	256K/1M	Pins 1 & 2, 3 & 4 closed	
411000	256K/1M	Pins 2 & 3, 4 & 5 closed	
441000	Any chip type	Pins 1 & 2, 3 & 4 closed	
Any chip type	4M	Pins 2 & 3, 4 & 5 closed	

Continued on next page. . .

AMERICAN MEGATRENDS, INC. 386 AT MARK II SYSTEM MOTHERBOARD

. . . continued from previous page

DRAM CONFIGURATION			
Size	Size Bank 2 Bank 3		
8MB	(18) 411000	(18) 411000	

DRAM SWITCH CONFIGURATION				
Mark II memory	BASE board memory	SW/1	SW/2	SW/3
640KB	1 bank	Off	On	On
896KB	2 banks	On	On	On
1664KB	1 bank	Off	Off	On
1920KB	2 banks	On	Off	On
3712KB	1 bank	Off	On	On
3968KB	2 banks	On	On	On
4736KB	1 bank	Off	On	Off
4992KB	2 banks	On	On	Off
7808KB	1 bank	Off	Off	On
8064KB	2 banks	On	Off	On
N/A*	2 banks	On	Off	Off

Note: * = Memory configuration in the 14MB & 15MB region is enabled. For all other configurations, the region is disabled.