

COMPAQ COMPUTER CORPORATION  
 PROLINEA 5120/5133/5150/5166

<b>Processor</b>	Pentium
<b>Processor Speed</b>	75/90/100/120/125/133/150/166MHz
<b>Chip Set</b>	Unidentified
<b>Video Chip Set</b>	Unidentified
<b>Maximum Onboard Memory</b>	192MB (EDO supported)
<b>Maximum Video Memory</b>	6MB
<b>Cache</b>	256KB
<b>BIOS</b>	Unidentified
<b>Dimensions</b>	330mm x 218mm
<b>I/O Options</b>	Unidentified
<b>NPU Options</b>	None

34371

CONNECTIONS	
Purpose	Location
External battery	P3
Note: The location and types of I/O options are unidentified.	

USER CONFIGURABLE SETTINGS		
Function	Label	Position
Battery type select internal	E5	Pins 1 & 2 closed
Battery type select external	E5	Pins 2 & 3 closed
Password enabled	E6	Pins 1 & 2 closed
Password disabled	E6	Pins 2 & 3 closed

DRAM CONFIGURATION			
Size	Bank 0	Bank 1	Bank 2
8MB	(2) 1M x 36	None	None
16MB	(2) 1M x 36	(2) 1M x 36	None
16MB	(2) 2M x 36	None	None
24MB	(2) 2M x 36	(2) 1M x 36	None
24MB	(2) 1M x 36	(2) 1M x 36	(2) 1M x 36
32MB	(2) 4M x 36	None	None
32MB	(2) 2M x 36	(2) 2M x 36	None
40MB	(2) 4M x 36	(2) 1M x 36	None
48MB	(2) 4M x 36	(2) 2M x 36	None
48MB	(2) 4M x 36	(2) 1M x 36	(2) 1M x 36
64MB	(2) 8M x 36	None	None
64MB	(2) 4M x 36	(2) 4M x 36	None
80MB	(2) 8M x 36	(2) 2M x 36	None
96MB	(2) 8M x 36	(2) 4M x 36	None
96MB	(2) 4M x 36	(2) 4M x 36	(2) 4M x 36
128MB	(2) 8M x 36	(2) 8M x 36	None
192MB	(2) 8M x 36	(2) 8M x 36	(2) 8M x 36
Note: Board accepts EDO memory.			

Continued on next page. . .

COMPAQ COMPUTER CORPORATION  
PROLINEA 5120/5133/5150/5166

... continued from previous page

**CACHE CONFIGURATION**

Note: The location of the cache is unidentified.

**VIDEO MEMORY CONFIGURATION**

Note: The location of the video memory is unidentified.

**CPU SPEED SELECTION**

CPU speed	Clock speed	Multiplier	S1/1	S1/2	S1/3	S1/4
75MHz	50MHz	1.5x	On	Off	Off	Off
90MHz	60MHz	1.5x	Off	Off	Off	Off
100MHz	66MHz	1.5x	Off	Off	On	Off
100MHz	50MHz	2x	On	On	Off	Off
120MHz	60MHz	2x	Off	On	Off	Off
125MHz	50MHz	2.5x	On	On	Off	On
133MHz	66MHz	2x	Off	On	On	Off
150MHz	60MHz	2.5x	Off	On	Off	On
166MHz	66MHz	2.5x	Off	On	On	On

**TECHNICAL NOTE**

Diagram not available.