

6I815EPT



Adopt INTEL 815EP B-step chipset, support Intel latest Tualatin CPU. for your processor , internal Storage and AGP provide the strongest support. humanized design, Intelligent system monitoring, support CNR slot, built-in sound card.

PROCESSOR

-Support Intel Socket 370 structure Celeron II (CeleronII), the latest Pentium 3rd generation Tualatin and VIA Cyrix III 66/100/133MHz FSB CPU.

CHIPSET

Uses Intel FW82815EP B-step and FW82801BA B-step chipsets.

SYSTEM MEMORY

-3 x 168pin 3.3V DIMM Socket
-Maximum support 512MB SDRAM

EIDE

- * Supports up to four IDE hard drives or optical drives .
- * Support PIO Mode 4 transfer rate up to 14 MB/ s .
- * Support Ultra DMA 33/66/100 (UDMA) transfer rate up to 33/66/100 MB/ s .

I/O ON BOARD

- *1 x FDD Port
- *1 x Printer Port
- *2 x Serial Port
- *1 x VGA Port (for P3SAE, and P3SAE-L)
- *1 x SIR Connector (Cable Option)
- *1 x PS/2 Mouse Connector
- *1 x PS/2 Keyboard Connector
- *4 x USB Ports (Cable Optional)
- *1 x Game Port
- *1 x Line in/ Line out/ MIC

VIDEO

Audio

*Audio Codec On Board

*AC97 Rev2.1 Spec Compatible

Slots

*1 x AGP Slot (Supporting Universal 4X AGP or AIMM)