

AFOX IG41-MA2

Model Name: IG41-MA2

Chipset: Intel® G41 Express Chipset + ICH7

Socket: INTEL® Socket 775

Supports Intel Core™ 2 Duo / Core™ Duo / Pentium® D / Pentium® 4 / Celeron® D Processors

Dual channel DDR3, two memory slots


1066 / 1333 / 1600MHz Memory up to 8GB

High speed USB interface

High quality audio special capacitor+independent audio block LED isolation line

Competent for multiple office needs

Low power consumption but high efficiency


[DESCRIPTION](#)
[SPECIFICATION](#)
[BIOS / DRIVERS UPDATE](#)
[REQUIREMENT](#)

Platform	Intel® Socket 775
Model Name	IG41-MA2
Chipset	Intel® G41 Express Chipset + ICH7
CPU Supports	Intel Core™ 2 Duo / Core™ Duo / Pentium® D / Pentium® 4 / Celeron® D Processors
FSB	1066 / 1333 / 1600MHz
Memory	Dual Channel DDR3 1066 / 1333 / 1600MHz
Dimm	2 x Memory Slots (Max. capacity of system memory 8GB) Actual capacity depends on different CPU installation
Onboard Graphics	Integrated Intel® GMA X4500 graphics
PCI/PCI-E Slots	1 x PCI Express x16 slot, 1 x PCI slot
SATA	4 x SATA2
IDE	1 x IDE
Audio	Realtek 662 on board, Supports 6-channel audio-out
LAN	Realtek RTL8105 10/100Mbps Ethernet on board
Back Panel I/Os	1 x D-Sub (VGA) 6 x USB 2.0 Ports 1 x RJ-45 LAN Port 3 x HD Audio Jacks (Line in / Front Speaker / Microphone)
ON-Board Pinheaders/Connectors	1 x USB 2.0 pinheader (supports additional 2 USB 2.0s)
BIOS	Supports BIOS update
Form Factor	Micro-ATX (17 x 21 cm)
Mounting	6 mounting holes
Accessories	1 x SATA II cable 1 x I/O Rear Panel 1 x User Manual 1 x Driver CD

PRODUCT

[Graphics Card](#)

[Motherboard](#)

[Mining Rig System](#)

[Memory](#)

[SSD](#)

[CPU Cooler](#)

[Power Supply](#)

[Mini PC](#)

NEWS

[Hot News](#)

[Product Review](#)

[Event & Promotion](#)

SERVICE & SUPPORT

[Warranty Policy](#)

[Download Center](#)

ABOUT AFOX

[About AFOX](#)

[公司简介](#)

[Certificate](#)