



(rev. 1.0)

[Overview](#)
[Specification](#)
[Support](#)
[News & Awards](#)
[Buy](#)
[Downloads](#)
[CPU Support](#)
[Manual](#)
[Support List](#)
[FAQ](#)
[Online Support](#)

CPU Support

Socket 775 - Intel P35

N/A = Not support

Socket 775								Model
Motherboard								PCB
Vendor	CPU Model	Frequency	L2 Cache	Core Name	Process	Stepping	Wattage	System Bus(MT/s)
Intel	Core™ 2 Extreme QX9770	3.20GHz	12MB	Yorkfield	45nm	C1	135W	1600
Intel	Core™ 2 Extreme QX9770	3.20GHz	12MB	Yorkfield	45nm	C0	135W	1600
Intel	Core™ 2 Extreme QX9650	3.00GHz	12MB	Yorkfield	45nm	C1	130W	1333
Intel	Core™ 2 Extreme QX9650	3.00GHz	12MB	Yorkfield	45nm	C0	130W	1333
Intel	Core™ 2 Quad Q9650	3.00GHz	12MB	Yorkfield	45nm	E0	95W	1333
Intel	Core™ 2	2.83GHz	12MB	Yorkfield	45nm	E0	95W	1333

GA-P35-S3G

(rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)

Intel	Quad Q9550	2.83GHz	12MB	Yorkfield	45nm	C1	95W	1333
Intel	Core™ 2 Quad Q9505s	2.83GHz	6MB	Yorkfield	45nm	R0	65W	1333
Intel	Core™ 2 Quad Q9505	2.83GHz	6MB	Yorkfield	45nm	R0	95W	1333
Intel	Core™ 2 Quad Q9500	2.83GHz	6MB	Yorkfield	45nm	R0	95W	1333
Intel	Core™ 2 Quad Q9450	2.66GHz	12MB	Yorkfield	45nm	C1	95W	1333
Intel	Core™ 2 Quad Q9400	2.66GHz	6MB	Yorkfield	45nm	R0	95W	1333
Intel	Core™ 2 Quad Q9400s	2.66GHz	6MB	Yorkfield	45nm	R0	65W	1333
Intel	Core™ 2 Quad Q9300	2.50GHz	6MB	Yorkfield	45nm	M1	95W	1333
Intel	Core™ 2 Quad Q8400	2.66GHz	4MB	Yorkfield	45nm	R0	95W	1333
Intel	Core™ 2 Quad Q8400s	2.66GHz	4MB	Yorkfield	45nm	R0	65W	1333
Intel	Core™ 2 Quad Q8300	2.50GHz	4MB	Yorkfield	45nm	R0	95W	1333
Intel	Core™ 2	2.33GHz	4MB	Yorkfield	45nm	M1	95W	1333

GA-P35-S3G

(rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)

Intel	Quad Q8200s	2.33GHz	4MB	Yorkfield	45nm	M1	65W	1333
Intel	Core™ 2 Duo E8600	3.33GHz	6MB	Wolfdale	45nm	E0	65W	1333
Intel	Core™ 2 Duo E8500	3.16GHz	6MB	Wolfdale	45nm	C0	65W	1333
Intel	Core™ 2 Duo E8500	3.16GHz	6MB	Wolfdale	45nm	E0	65W	1333
Intel	Core™ 2 Duo E8400	3.00GHz	6MB	Wolfdale	45nm	C0	65W	1333
Intel	Core™ 2 Duo E8400	3.00GHz	6MB	Wolfdale	45nm	E0	65W	1333
Intel	Core™ 2 Duo E8300	2.83GHz	6MB	Wolfdale	45nm	C0	65W	1333
Intel	Core™ 2 Duo E8200	2.66GHz	6MB	Wolfdale	45nm	C0	65W	1333
Intel	Core™ 2 Duo E8190	2.66GHz	6MB	Wolfdale	45nm	C0	65W	1333
Intel	Core™ 2 Extreme QX6850	3.00GHz	8MB	Kentsfield	65nm	G0	130W	1333
Intel	Core™ 2 Extreme QX6800	2.93GHz	8MB	Kentsfield	65nm	G0	130W	1066
Intel	Core™ 2	2.66GHz	8MB	Kentsfield	65nm	B3	130W	1066

GA-P35-S3G

(rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)

Intel	Quad Q6700	2.66GHz	8MB	Kentsfield	65nm	G0	95W	1066
Intel	Core™ 2 Quad Q6600	2.40GHz	8MB	Kentsfield	65nm	G0	95W	1066
Intel	Core™ 2 Quad Q6600	2.40GHz	8MB	Kentsfield	65nm	B3	105W	1066
Intel	Core™ 2 Duo E7600	3.06GHz	3MB	Wolfdale	45nm	R0	65W	1066
Intel	Core™ 2 Duo E7500	2.93GHz	3MB	Wolfdale	45nm	R0	65W	1066
Intel	Core™ 2 Duo E7400	2.80GHz	3MB	Wolfdale	45nm	R0	65W	1066
Intel	Core™ 2 Duo E7300	2.66GHz	3MB	Wolfdale	45nm	M0	65W	1066
Intel	Core™ 2 Duo E7200	2.53GHz	3MB	Wolfdale	45nm	M0	65W	1066
Intel	Core™ 2 Duo E6850	3.00GHz	4MB	Conroe	65nm	G0	65W	1333
Intel	Core™ 2 Duo E6750	2.66GHz	4MB	Conroe	65nm	G0	65W	1333
Intel	Core™ 2 Duo E6700	2.66GHz	4MB	Conroe	65nm	B2	65W	1066
Intel	Core™ 2	2.40GHz	4MB	Conroe	65nm	B2	65W	1066

GA-P35-S3G

(rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)

Intel	Duo E6540	2.33GHz	4MB	Conroe	65nm	G0	65W	1333
Intel	Core™ 2 Duo E6420	2.13GHz	4MB	Conroe	65nm	B2	65W	1066
Intel	Core™ 2 Duo E6400	2.13GHz	2MB	Conroe	65nm	L2	65W	1066
Intel	Core™ 2 Duo E6400	2.13GHz	2MB	Conroe	65nm	B2	65W	1066
Intel	Core™ 2 Duo E6320	1.86GHz	4MB	Conroe	65nm	B2	65W	1066
Intel	Core™ 2 Duo E6300	1.86GHz	2MB	Conroe	65nm	L2	65W	1066
Intel	Core™ 2 Duo E6300	1.86GHz	2MB	Conroe	65nm	B2	65W	1066
Intel	Core™ 2 Duo E4700	2.60GHz	2MB	Conroe	65nm	G0	65W	800
Intel	Core™ 2 Duo E4600	2.40GHz	2MB	Conroe	65nm	M0	65W	800
Intel	Core™ 2 Duo E4500	2.20GHz	2MB	Conroe	65nm	M0	65W	800
Intel	Core™ 2 Duo E4400	2.00GHz	2MB	Conroe	65nm	M0	65W	800
Intel	Core™ 2	2.00GHz	2MB	Conroe	65nm	L2	65W	800

GA-P35-S3G

(rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)

Intel	Dual-Core E6800	3.33GHz	2MB	Wolfdale	45nm	R0	65W	1066
Intel	Pentium Dual-Core E6700	3.20GHz	2MB	Wolfdale	45nm	R0	65W	1066
Intel	Pentium Dual-Core E6600	3.06GHz	2MB	Wolfdale	45nm	R0	65W	1066
Intel	Pentium Dual-Core E6500	2.93GHz	2MB	Wolfdale	45nm	R0	65W	1066
Intel	Pentium Dual-Core E6300	2.80GHz	2MB	Wolfdale	45nm	R0	65W	1066
Intel	Pentium Dual-Core E5800	3.20GHz	2MB	Wolfdale	45nm	R0	65W	800
Intel	Pentium Dual-Core E5700	3.00GHz	2MB	Wolfdale	45nm	R0	65W	800
Intel	Pentium Dual-Core E5500	2.80GHz	2MB	Wolfdale	45nm	R0	65W	800
Intel	Pentium Dual-Core E5400	2.70GHz	2MB	Wolfdale	45nm	R0	65W	800
Intel	Pentium Dual-Core E5300	2.60GHz	2MB	Wolfdale	45nm	R0	65W	800
Intel	Pentium Dual-Core E5200	2.50GHz	2MB	Wolfdale	45nm	R0	65W	800
Intel	Pentium	2.50GHz	2MB	Wolfdale	45nm	M0	65W	800

GA-P35-S3G

(rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)

Intel	Dual-Core E2200	2.20GHz	1MB	Conroe	65nm	M0	65W	800
Intel	Pentium Dual-Core E2180	2.00GHz	1MB	Conroe	65nm	M0	65W	800
Intel	Pentium Dual-Core E2160	1.80GHz	1MB	Conroe	65nm	M0	65W	800
Intel	Pentium Dual-Core E2160	1.80GHz	1MB	Conroe	65nm	L2	65W	800
Intel	Pentium Dual-Core E2140	1.60GHz	1MB	Conroe	65nm	M0	65W	800
Intel	Pentium Dual-Core E2140	1.60GHz	1MB	Conroe	65nm	L2	65W	800
Intel	Celeron Dual-Core E3500	2.70GHz	1MB	Wolfdale	45nm	R0	65W	800
Intel	Celeron Dual-Core E3400	2.60GHz	1MB	Wolfdale	45nm	R0	65W	800
Intel	Celeron Dual-Core E3300	2.50GHz	1MB	Wolfdale	45nm	R0	65W	800
Intel	Celeron Dual-Core E3200	2.40GHz	1MB	Wolfdale	45nm	R0	65W	800
Intel	Celeron Dual-Core E1600	2.40GHz	512KB	Conroe	65nm	M0	65W	800
Intel	Celeron	2.20GHz	512KB	Conroe	65nm	M0	65W	800

GA-P35-S3G

(rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)

Intel	Dual-Core E1200	1.60GHz	512KB	Conroe	65nm	M0	65W	800
Intel	Pentium Extreme Edition 965	3.73GHz	4MB	Presler	65nm	C1	130W	1066
Intel	Pentium Extreme Edition 955	3.46GHz	4MB(2x2)	Presler	65nm	B1	130W	1066
Intel	Pentium Extreme Edition 840-XE	3.20GHz	2MB	Smithfield	90nm	A0	130W	800
Intel	Pentium D 960	3.60GHz	4MB	Presler	65nm	D0	95W	800
Intel	Pentium D 960	3.60GHz	4MB(2x2)	Presler	65nm	C1	130W	800
Intel	Pentium D 950	3.40GHz	4MB(2x2)	Presler	65nm	B1	130W	800
Intel	Pentium D 945	3.40GHz	4MB	Presler	65nm	D0	95W	800
Intel	Pentium D 945	3.40GHz	4MB	Presler	65nm	C1	95W	800
Intel	Pentium D 940	3.20GHz	4MB	Presler	65nm	C1	95W	800
Intel	Pentium D 940	3.20GHz	4MB(2x2)	Presler	65nm	B1	130W	800
Intel	Pentium D 935	3.20GHz	4MB	Presler	65nm	D0	95W	800
Intel	Pentium D 930	3.00GHz	4MB	Presler	65nm	C1	95W	800

GA-P35-S3G

(rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)

Intel	Pentium D 915	2.80GHz	4MB	Presler	65nm	C1	95W	800
Intel	Pentium D 840	3.20GHz	2MB	Smithfield	90nm	B0	130W	800
Intel	Pentium D 840	3.20GHz	2MB	Smithfield	90nm	A0	130W	800
Intel	Pentium D 830	3.00GHz	2MB	Smithfield	90nm	B0	130W	800
Intel	Pentium D 830	3.00GHz	2MB	Smithfield	90nm	A0	130W	800
Intel	Pentium D 820	2.80GHz	2MB	Smithfield	90nm	B0	95W	800
Intel	Pentium D 820	2.80GHz	2MB	Smithfield	90nm	A0	95W	800
Intel	Pentium D 805	2.66GHz	2MB	Smithfield	90nm	B0	95W	533
Intel	P4-Extreme Edition	3.73GHz	2MB	Prescott	90nm	N0	115W	1066
Intel	P4-Extreme Edition	3.46GHz	2MB	Northwood	130nm	M0	110.7W	1066
Intel	P4-Extreme Edition	3.40GHz	2MB	Northwood	130nm	M0	109.6W	800
Intel	Pentium 4 672	3.80GHz	2MB	Prescott	90nm	R0	115W	800
Intel	Pentium 4 670	3.80GHz	2MB	Prescott	90nm	R0	115W	800
Intel	Pentium 4 670	3.80GHz	2MB	Prescott	90nm	N0	115W	800

GA-P35-S3G

(rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)

Intel	Pentium 4 651	3.40GHz	2MB	Cedar Mill	65nm	D0	65W	800
Intel	Pentium 4 651	3.40GHz	2MB	Cedar Mill	65nm	B1	86W	800
Intel	Pentium 4 650	3.40GHz	2MB	Prescott	90nm	R0	84W	800
Intel	Pentium 4 650	3.40GHz	2MB	Prescott	90nm	N0	84W	800
Intel	Pentium 4 641	3.20GHz	2MB	Cedar Mill	65nm	D0	65W	800
Intel	Pentium 4 641	3.20GHz	2MB	Cedar Mill	65nm	B1	86W	800
Intel	Pentium 4 640	3.20GHz	2MB	Prescott	90nm	N0	84W	800
Intel	Pentium 4 631	3.00GHz	2MB	Cedar Mill	65nm	D0	65W	800
Intel	Pentium 4 631	3.00GHz	2MB	Cedar Mill	65nm	B1	86W	800
Intel	Pentium 4 630	3.00GHz	2MB	Prescott	90nm	N0	84W	800
Intel	Pentium 4 571	3.80GHz	1MB	Prescott	90nm	E0	115W	800
Intel	Pentium 4 570J	3.80GHz	1MB	Prescott	90nm	E0	115W	800
Intel	Pentium 4 561	3.60GHz	1MB	Prescott	90nm	E0	115W	800
Intel	Pentium 4 560	3.60GHz	1MB	Prescott	90nm	D0	115W	800
Intel	Pentium 4 560J	3.60GHz	1MB	Prescott	90nm	E0	115W	800

GA-P35-S3G

(rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)

Intel	Pentium 4 550J	3.40GHz	1MB	Prescott	90nm	E0	84W	800
Intel	Pentium 4 541	3.20GHz	1MB	Prescott	90nm	E0	84W	800
Intel	Pentium 4 540	3.20GHz	1MB	Prescott	90nm	E0	84W	800
Intel	Pentium 4 531	3.00GHz	1MB	Prescott	90nm	E0	84W	800
Intel	Pentium 4 530	3.00GHz	1MB	Prescott	90nm	D0	84W	800
Intel	Pentium 4 530J	3.00GHz	1MB	Prescott	90nm	E0	84W	800
Intel	Pentium 4 524	3.06GHz	1MB	Prescott	90nm	G1	84W	533
Intel	Pentium 4 521	2.80GHz	1MB	Prescott	90nm	E0	84W	800
Intel	Pentium 4 520	2.80GHz	1MB	Prescott	90nm	D0	84W	800
Intel	Pentium 4 519K	3.06GHz	1MB	Prescott	90nm	G1	84W	533
Intel	Pentium 4 516	2.93GHz	1MB	Prescott	90nm	G1	84W	533
Intel	Pentium 4 516	2.93GHz	1MB	Prescott	90nm	E0	84W	533
Intel	Pentium 4 506	2.66GHz	1MB	Prescott	90nm	E0	84W	533
Intel	Pentium 4 505J	2.66GHz	1MB	Prescott	90nm	E0	84W	533
Intel	Celeron 400	2.00GHz	512KB	Conroe-L	65nm	A1	35W	800

GA-P35-S3G

(rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)

Intel	Celeron 400 Sequence 420	1.60GHz	512KB	Conroe-L	65nm	A1	35W	800
Intel	Celeron D 365	3.60GHz	512KB	Cedar Mill	65nm	D0	65W	533
Intel	Celeron D 360	3.46GHz	512KB	Cedar Mill	65nm	D0	65W	533
Intel	Celeron D 356	3.33GHz	512KB	Cedar Mill	65nm	C1	86W	533
Intel	Celeron D 355	3.33GHz	256KB	Prescott	90nm	G1	73W	533
Intel	Celeron D 352	3.20GHz	512KB	Cedar Mill	65nm	C1	86W	533
Intel	Celeron D 351	3.20GHz	256KB	Prescott	90nm	E0	84W	533
Intel	Celeron D 346	3.06GHz	256KB	Prescott	90nm	E0	84W	533
Intel	Celeron D 345J	3.06GHz	256KB	Prescott	90nm	E0	84W	533
Intel	Celeron D 341	2.93GHz	256KB	Prescott	90nm	E0	84W	533
Intel	Celeron D 340J	2.93GHz	256KB	Prescott	90nm	E0	84W	533
Intel	Celeron D 336	2.80GHz	256KB	Prescott	90nm	E0	84W	533
Intel	Celeron D 335J	2.80GHz	256KB	Prescott	90nm	E0	84W	533
Intel	Celeron D 331	2.66GHz	256KB	Prescott	90nm	E0	84W	533
Intel	Celeron D	2.66GHz	256KB	Prescott	90nm	E0	84W	533

GA-P35-S3G

(rev. 1.0)

Overview Specification Support News & Awards Buy

Clear All

#1. Download speed may be varied in different region. If you have experienced lower download speed, please try other region download sites.

#2. Please download from the region "**Asia**" if the file you wanted to download does not exist in other region.

#3. If you have encountered problems or cannot find the file after following #2, please feedback to our Technical Service for further help.

#4. For better download quality, it is recommended to use software like Flashget or Getright to monitor your file download status for saving your treasure time and efforts.

COMPANY	CONSUMER	ENTERPRISE	SOLUTION	SERVICE / SUPPORT
About Us	Motherboard	Server Motherboard	Application Solutions	Product Support
CSR	Graphics Card	Rack Server	Industry Solutions	Online Support
News	Laptop	GPU Server		FAQ
Career	Monitor	High Density Server	RESOURCE	Warranty
Investor	Desktop PC	Advanced Cooling	Insight	
Contact Us	PC Peripherals	ARM Server	Success Case	
	PC Components	Storage Server	Awards	
		Edge Server	News	
		Tower Server / Workstation	Events	
		Embedded Computing		
		e-Mobility		

GA-P35-S3G (rev. 1.0)

[Overview](#) [Specification](#) [Support](#) [News & Awards](#) [Buy](#)

[Clear All](#)