


IGVMP

Intel 82845GV CHIPSET With Integrated 2D/3D Graphic & 6-CH Audio /ATA100 /LAN /USB2.0 support 478 Pin Pentium 4 Micro ATX Main Board

Integrated 3D Graphic /USB2.0 /6-CH Audio Solution



Processor

- PGA 478B Socket for Intel Pentium®4 478 Pin FCPGA2 package processor, support 400/533MHz System Bus Frequency (Support Hyper-Threading CPU)

Chipset

- Intel 845GV Graphics Memory Controller Hub (GMCH)
- Intel 82801DB I/O Controller Hub (ICH4)

Expansion Slot

- Support 3xPCI Slot

System Memory

- 2 x 184-pin DDR DIMM Sockets Support max 2GB 2.5V unbuffered DDR SDRAM
- Support Up to 2 un-buffer DDR200/DDR266/DDR333 DIMM

Jumpless

- Support Jumpless function by BIOS SETUP let users more easier change the Frequency and ratio

Integrated Graphics Controller

- 256 bit graphics core
- Integrated 2D/3D graphics accelerator
- Intel Digital Video Out (DVO) ports add Support for digital displays and TV-Out
- Integrated 350MHz RAMDAC
- Support ADD (AGP Digital Display) card

Magic Setting

- Support CPU Front Side Bus step by step setting in BIOS SETUP let users have many choice when use over-clock function

PCI LAN

- VIA VT6105 PCI LAN controller chip
- IEEE 802.3 10/100 BASE T Standards
- BIOS Boot-up from LAN

Ultra DMA 100

- Support 2 x Ultra DMA 100 IDE Interface (Up to 4 IDE Devices & 100MB/s transfer rate)
- ATAPI IDE CD-ROM, CD-R, CD-RW and LS-120 Support

PC'99 Colorful I/O Ports

- 6xUSB 2.0 Ports, 2xSerial, 1xParallel Port
- 1xPS/2 Keyboard, 1xPS/2 Mouse Port, 1xFloppy Port
- 1x Line-in/out/MIC Ports

On Board Audio

- Software Audio Controller with Onboard 6-Channel CODEC Compliant to AC97'
- Support 3D Surround & Positioning, Full Duplex

Dimension

Micro ATX form factor (24.4cm x 19.0cm)

Special Function

- ACPI supporting for OS Directed Power Management
 - MODEM Ring remote wake up
 - RTC Alarm, Keyboard Power On
- PC Health Monitor CPU temperature, System temperature, System Voltage (Vcore, Vtt, Vcc3, 5V, 12V...), FAN speed
- Support earphone amplifier
- Magic Install CD for user install Driver easily
- Magic BIOS Utility support live Update BIOS function from web

Trademark

- * Product and Company names mentioned herein may be the trademarks of their respective owners.